US008489819B2

(12) **United States Patent**
Guthrie et al.

(10) **Patent No.: US 8,489,819 B2**
(45) **Date of Patent: *Jul. 16, 2013**

(54) **VICTIM CACHE LATERAL CASTOUT TARGETING**

(75) Inventors: **Guy L. Guthrie**, Austin, TX (US); **Michael S. Siegel**, Raleigh, NC (US); **William J. Starke**, Round Rock, TX (US); **Derek E. Williams**, Austin, TX (US)

(73) Assignee: **International Business Machines Corporation**, Armonk, NY (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 858 days.

This patent is subject to a terminal disclaimer.

(21) Appl. No.: **12/340,511**

(22) Filed: **Dec. 19, 2008**

(65) **Prior Publication Data**

US 2010/0235577 A1 Sep. 16, 2010

(51) **Int. Cl.**
G06F 12/00 (2006.01)
G06F 13/00 (2006.01)
G06F 13/28 (2006.01)

(52) **U.S. Cl.**
USPC **711/133**; 711/122; 711/E12.022; 711/E12.024

(58) **Field of Classification Search**
USPC 711/133, 122, E12.022, E12.024
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,797,814 A 1/1989 Brenza
5,615,350 A 3/1997 Hesson et al.
5,666,506 A 9/1997 Hesson et al.
5,721,921 A 2/1998 Kessler et al.
5,764,946 A 6/1998 Tran et al.
5,802,571 A 9/1998 Konigsburg et al.
5,835,946 A 11/1998 Allen et al.

(Continued)

FOREIGN PATENT DOCUMENTS

JP 09050401 2/1997
JP 2000207283 7/2000

(Continued)

OTHER PUBLICATIONS

U.S. Appl. No. 11/056,649, filed Feb. 12, 2005, First Named Inventor Leo James Clark, Non-Final Office Action dated Mar. 8, 2007.

(Continued)

Primary Examiner — Sheng-Jen Tsai
(74) *Attorney, Agent, or Firm* — Yudell Isidore Ng Russell PLLC

(57) **ABSTRACT**

A data processing system includes a plurality of processing units coupled by an interconnect fabric. In response to a data request, a victim cache line is selected for castout from a first lower level cache of a first processing unit, and a target lower level cache of one of the plurality of processing units is selected based upon architectural proximity of the target lower level cache to a home system memory to which the address of the victim cache line is assigned. The first processing unit issues on the interconnect fabric a lateral castout (LCO) command that identifies the victim cache line to be castout from the first lower level cache and indicates that the target lower level cache is an intended destination. In response to a coherence response indicating success of the LCO command, the victim cache line is removed from the first lower level cache and held in the second lower level cache.

25 Claims, 21 Drawing Sheets



U.S. PATENT DOCUMENTS

5,848,433	A	12/1998	Tran et al.	
5,895,495	A	4/1999	Arimilli et al.	
5,970,232	A	10/1999	Passint et al.	
6,059,835	A	5/2000	Bose	
6,085,303	A	7/2000	Thorson et al.	
6,088,771	A	7/2000	Steely et al.	
6,131,145	A	10/2000	Matsubara et al.	
6,216,174	B1	4/2001	Scott et al.	
6,226,713	B1	5/2001	Mehrotra	
6,230,252	B1	5/2001	Passint et al.	
6,230,260	B1	5/2001	Luick	
6,240,490	B1	5/2001	Lyles, Jr.	
6,272,598	B1	8/2001	Arlitt et al.	
6,275,909	B1	8/2001	Arimilli et al.	
6,282,615	B1	8/2001	Arimilli et al.	
6,343,347	B1 *	1/2002	Arimilli et al.	711/143
6,343,348	B1	1/2002	Tremblay et al.	
6,356,980	B1	3/2002	Arimilli et al.	
6,397,296	B1	5/2002	Werner	
6,408,345	B1	6/2002	Fuoco et al.	
6,446,167	B1	9/2002	Mayfield et al.	
6,453,389	B1	9/2002	Weinberger et al.	
6,460,115	B1	10/2002	Kahle et al.	
6,502,171	B1	12/2002	Arimilli et al.	
6,532,521	B1	3/2003	Arimilli et al.	
6,542,861	B1	4/2003	Lyles, Jr.	
6,546,429	B1	4/2003	Baumgartner et al.	
6,587,924	B2	7/2003	Arimilli et al.	
6,643,763	B1	11/2003	Starke et al.	
6,647,466	B2	11/2003	Steely	
6,654,946	B1	11/2003	Eneboe et al.	
6,675,253	B1 *	1/2004	Brinkmann et al.	710/316
6,691,220	B1	2/2004	Guthrie et al.	
6,748,501	B2	6/2004	Arimilli et al.	
6,748,518	B1	6/2004	Guthrie et al.	
6,751,698	B1	6/2004	Deneroff et al.	
6,757,294	B1 *	6/2004	Maruyama	370/432
6,810,466	B2	10/2004	Henry et al.	
6,963,967	B1	11/2005	Guthrie et al.	
6,990,559	B2	1/2006	Van Doren et al.	
7,028,159	B2	4/2006	Matsubara et al.	
7,047,362	B2	5/2006	Kim et al.	
7,047,394	B1	5/2006	Van Dyke et al.	
7,065,672	B2	6/2006	Long et al.	
7,100,021	B1	8/2006	Marshall et al.	
7,146,468	B2	12/2006	Hardage, Jr.	
7,155,572	B2	12/2006	Hughes et al.	
7,174,431	B2	2/2007	Van Doren et al.	
7,228,385	B2	6/2007	Guthrie et al.	
7,254,678	B2	8/2007	Alexander et al.	
7,281,092	B2 *	10/2007	Rajamony et al.	711/122
7,305,522	B2	12/2007	Clark et al.	
7,305,523	B2	12/2007	Guthrie et al.	
7,305,524	B2	12/2007	Hoover	
7,406,086	B2	7/2008	Deneroff et al.	
7,437,521	B1	10/2008	Scott et al.	
7,454,573	B2	11/2008	Buyuktosunoglu et al.	
7,461,147	B1 *	12/2008	Mowat et al.	709/225
7,475,191	B2	1/2009	Guthrie et al.	
7,533,227	B2	5/2009	Guthrie et al.	
7,536,513	B2	5/2009	Guthrie et al.	
7,584,329	B2	9/2009	Fields, Jr.	
7,613,883	B2	11/2009	Bellows et al.	
7,716,424	B2	5/2010	Franaszek et al.	
7,788,468	B1	8/2010	Nickolls et al.	
7,797,496	B2	9/2010	Gruber et al.	
7,827,354	B2	11/2010	Clark et al.	
8,347,036	B2 *	1/2013	Cargnoni et al.	711/118
2002/0046324	A1	4/2002	Barroso et al.	
2004/0034744	A1 *	2/2004	Karlsson et al.	711/133
2004/0103251	A1	5/2004	Alsup	
2005/0086438	A1 *	4/2005	Peterson et al.	711/141
2005/0120185	A1	6/2005	Yamazaki et al.	
2005/0246499	A1	11/2005	Salida et al.	
2006/0039612	A1 *	2/2006	Sakuma et al.	382/225
2006/0064549	A1	3/2006	Wintergerst	
2006/0101249	A1	5/2006	Bacon et al.	
2006/0112228	A1	5/2006	Shen	
2006/0155792	A1	7/2006	Inoue et al.	
2006/0179234	A1	8/2006	Bell et al.	
2006/0184742	A1	8/2006	Clark et al.	
2006/0225074	A1	10/2006	Vaid et al.	
2006/0277366	A1 *	12/2006	Rajamony et al.	711/133
2007/0073974	A1	3/2007	Averill et al.	
2007/0094450	A1	4/2007	VanderWiel	
2007/0136535	A1 *	6/2007	Rajamony et al.	711/143
2007/0204110	A1	8/2007	Guthrie et al.	
2007/0294481	A1	12/2007	Hoover	
2008/0046651	A1	2/2008	Clark et al.	
2008/0046736	A1	2/2008	Arimilli et al.	
2008/0071994	A1	3/2008	Fields, Jr.	
2008/0086602	A1	4/2008	Guthrie et al.	
2008/0177953	A1	7/2008	Bell et al.	
2009/0177844	A1	7/2009	Naylor et al.	
2010/0100682	A1	4/2010	Guthrie et al.	
2010/0100683	A1	4/2010	Guthrie et al.	
2010/0122031	A1 *	5/2010	Strumpen et al.	711/122
2010/0146216	A1 *	6/2010	Conway	711/141
2010/0153647	A1	6/2010	Guthrie et al.	
2010/0153649	A1	6/2010	Li et al.	
2010/0153650	A1	6/2010	Guthrie et al.	
2010/0235576	A1	9/2010	Guthrie et al.	
2010/0235584	A1	9/2010	Guthrie et al.	
2010/0257316	A1	10/2010	Arimilli et al.	
2010/0257317	A1	10/2010	Arimilli et al.	
2010/0262778	A1 *	10/2010	Cargnoni et al.	711/118
2010/0262782	A1	10/2010	Guthrie et al.	
2010/0262783	A1	10/2010	Guthrie et al.	
2010/0262784	A1	10/2010	Guthrie et al.	
2011/0161589	A1	6/2011	Guthrie et al.	

FOREIGN PATENT DOCUMENTS

JP	2000242558	9/2000
JP	2000298618	10/2000
JP	2002236616	8/2002

OTHER PUBLICATIONS

U.S. Appl. No. 11/056,673, filed Feb. 12, 2005, First Named Inventor Guy L. Guthrie, Non-Final Office Action dated Mar. 9, 2007.

U.S. Appl. No. 11/923,952, filed Oct. 25, 2007, First Named Inventor Leo James Clark, Non-Final Office Action dated Aug. 20, 2008.

U.S. Appl. No. 12/402,025, "Lateral Castout (LCO) of Victim Cache Line in Data-Invalid State," Non-Final Office Action dated Jun. 30, 2011.

"Optimizing Memory-Resident Decision Support System Workloads for Cache Memories", Trancoso. PPM. 1998.

"Cache-Conscious Frequent Pattern Mining on Modern and Emerging Processors", Chen. Y-K. et al. ; 2007.

"Effective Management of Multiple Configurable Units Using Dynamic Optimization", Hu, S. et al. ; Dec. 2006.

U.S. Appl. No. 12/420,379, "Lateral Castout Target Selection," Non-Final Office Action dated Jul. 1, 2011.

"Deferring Cast-Outs n Store-In Caches", Emma, PG. et al.; Apr. 1, 1998.

"Value-Based Web Caching", Rhea, SC. Et al.; 2003.

Steiner et al.—"A Characterization of a Java Based Commercial Workload on a High-End Enterprise Server"; ACM Digital Library; pp. 379-380; Jun. 2006.

US Patent No. 7827354, "Victim Cache Using Direct Intervention," Notice of Allowance dated Jun. 30, 2010.

US Patent No. 7305522, "Victim Cache Using Direct Intervention," Notice of Allowance dated Jul. 30, 2007.

US Patent No. 7827354, "Victim Cache Using Direct Intervention," Non-Final Office Action dated Dec. 15, 2009.

US Patent No. 7305523, "Cache Memory Direct Intervention," Notice of Allowance dated Jul. 30, 2007.

US Patent No. 7827354, "Victim Cache Using Direct Intervention," Final Office Action dated Feb. 3, 2009.

Wang et al.—"Parallization of IBM Mambo System Simulator in Functional Modes"; ACM Digital Library; pp. 71-76; 2007-2008.

U.S. Appl. No. 12/335,975, "Cache-To-Cache Cast-In", Non-Final Office Action dated Jul. 1, 2011.

U.S. Appl. No. 12/421,017, "Empirically Based Dynamic Control of Acceptance of Victim Cache Lateral Castouts," Non-Final Office Action dated Jul. 27, 2011.
U.S. Appl. No. 12/421,180, "Empirically Based Dynamic Control of Transmission of Victim Cache Lateral Castouts," Non-Final Office Action dated Jul. 27, 2011.
U.S. Appl. No. 12/177,912, "Victim Cache Replacement", Non-Final Office Action dated Dec. 9, 2010.
U.S. Appl. No. 12/177,912, "Victim Cache Replacement", Final Office Action dated May 24, 2011.
Ko et al, Characterization and Design of a Low-Power, High-Performance Cache Architecture, Proceedings of Technical Papers, International Symposium on VLSI Technology, Systems and Applications, 1995, pp. 235-238, May-Jun. 1995.
Yang et al, Lightweight Set Buffer: Low Power Data Cache for Multimedia Application, Aug. 2003.
Chang et al, Value-Conscious Cache: Simple Technique for Reducing Cache Access Power, Proceedings of the Design, Automation, and Test in Europe Conference and Exhibition, 2004.
U.S. Appl. No. 12/256,064, "Victim Cache Replacement," Non-Final Office Action dated Jun. 8, 2011.
Sarkar, P. et al; Hint-Based Cooperative Caching; ACM Transactions on Computer Systems, vol. 18, No. 4, Nov. 2000, pp. 387-419.
Dybdahl, H. et al; An LRU-based Replacement Algorithm Augmented with Frequency of Access in Shared Chip-Multiprocessor Caches; ACM; 2006; pp. 45-52.
Kampe, M. et al; Self-Correcting LRU Replacement Policies; ACM; 2004; pp. 181-191.
Mellor-Crummey, J. et al; Algorithms for Scalable Synchronization on Shared-Memory Multiprocessors; ACM Transactions on Computer Systems, vol. 9, No. 1, Feb. 1991, pp. 21-65.
U.S. Appl. No. 12/256,002, "Victim Cache Replacement," Non-Final Office Action Jun. 15, 2011.
U.S. Appl. No. 12/402,025, "Lateral Castout (LCO) of Victim Cache Line in data-Invalid State", Final Office Action dated Nov. 10, 2011.
U.S. Appl. No. 12/335,975, "Cache-To-Cache Cast-In," Final Office Action dated Nov. 22, 2011.
U.S. Appl. No. 12/420,379, "Lateral Castout Target Selection," Final Office Action dated Nov. 22, 2011.
U.S. Appl. No. 12/419,343, "Virtual Barrier Synchronization Cache Castout Election," Notice of Allowance dated Sep. 2, 2011.
Berekovic et al; A Scalable, Clustered SMT Processor for Digital Signal Processing; ACM SIGARCH Computer Architecture News; vol. 32, No. 3, Jun. 2004, pp. 62-69.
Prabhu, M., et al; Using Thread-Level Speculation to Simply Manual Parallelization; ACM; 2003; pp. 1-12.
U.S. Appl. No. 12/419,364, "Virtual Barrier Synchronization Cache," Notice of Allowance dated Aug. 25, 2011.
U.S. Appl. No. 12/419,364, "Virtual Barrier Synchronization Cache," Notice of Allowance dated Oct. 21, 2011.
Raghavachari, M. et al; Ace: A Language for Parallel Programming With Customizable Protocols; ACM Transactions on Computer Systems, vol. 17, No. 3, Aug. 1999, pp. 202-248.
Fang, Z. et al; Active Memory Operations; ICS-2007, Seattle, WA, pp. 232-241.
Sampson,J. et al.; Exploiting Fine-Grained Data Parallelism with Chip Multiprocessors and Fast Barriers; The 39th Annual IEEE/ACM International Symposium on Microarchitecture (MICRO '06); 2006.
Yeung,D. et al; Multigrain Shared Memory; ACM Transactions on Computer Systems, vol. 18, No. 2, May 2000, pp. 154-196.
U.S. Appl. No. 12/420,933, "Mode-Based Castout Destination Selection," Non-Final Office Action dated Jul. 14, 2011.
Fei et al., "Artemis: Practical Runtime Monitoring of Applications for Execution Anomalies." Purdue University, 12 pp.; PLDI'06, Jun. 10-16, 2006, Ottawa, Ontario Canada.
Rhea et al., "Value-Based Web Caching," University of California, Berkeley, 10 pp.; WWW2003, May 20-24, 2003, Budapest, Hungary.
Shin et al., "A Proactive Wearout Recovery Approach for Exploiting Microarchitectural Redundancy to Extend Cache SRAM Lifetime." IBM T.J. Watson Research Center, Yorktown Heights, NY, 10 pp.; International Symposium on Computer Architecture—2008 IEEE.
Richardson, Nicholas,"Bus interface unit having multipurpose transaction buffer," 1 pp.; CSA Technology Research Database, Dialog File No. 23 Accession No. 8552866.
U.S. Appl. No. 12/336,048, "Handling Castout Cache Lines in a Victim Cache," Non-Final Office Action dated Nov. 30, 2011.
U.S. Appl. No. 12/335,809, "Victim Cache Line Selection," Notice of Allowance dated Oct. 5, 2011.
U.S. Appl. No. 12/421,180 entitled "Empirically Based Dynamic Control of Transmission of Victim Cache Lateral Castouts" Final Office Action dated Jan. 24, 2012.
U.S. Appl. No. 12/420,933 entitled "Mode-Based Cast Out Destination Selection", Notice of Allowance dated Jul. 5, 2012.
U.S. Appl. No. 12/256,064 entitled "Victim Cache Prefetching", Notice of Allowance dated Feb. 17, 2012.
U.S. Appl. No. 13/445,646 entitled "Selective Cache-To-Cache Lateral Castouts", Non-Final Office action dated Jul. 9, 2012.
U.S. Appl. No. 12/420,379 entitled "Lateral Castout Target Selection", Notice of Allowance dated Jun. 4, 2012.
U.S. Appl. No. 12/177,912 entitled "Victim Cache Replacement", Non-Final Office action dated Mar. 2, 2012.
U.S. Appl. No. 12/335,975 entitled "Lateral Cache-To-Cache Cast-In", Notice of Allowance dated Mar. 7, 2012, now Issued Patent 8225045 Jul. 17, 2012.
U.S. Appl. No. 12/256,002 entitled "Victim Cache Replacement", Final Office action dated Dec. 6, 2011.
U.S. Appl. No. 12/256,002 entitled "Victim Cache Replacement", Non-Final Office action dated Mar. 15, 2012.
U.S. Appl. No. 12/650,018 entitled "Selective Cache-To-Cache Lateral Castouts", Non-Final Office action dated Apr. 18, 2012.

* cited by examiner


100
110
Processing Node 102b
Processing Node 102a
PU 104b
PU 104d
PU 104a
PU 104c
System Memory 108b
System Memory 108a
System Memory 108d
System Memory 108c
114

Figure 1


I/O Device 216
I/O Controller 214
IMC 206
Interconnect Logic 212
Coherence Management Logic 210
Processor Core and Cache Hierarchy 200
Processing Unit 104

Figure 2A


200
Processor Core 202
Streaming Prefetcher 203
L1 Cache 204
Store Data 246
Store Req 244
Gathering Logic 248
Store Data 249
Store Req 247
Load Data 242
Load Req 240
L2 Cache 230
Load Req 260
Load Data 262
Cast-in Req 264
Cast-in Data 266
System Coherence Cmd 250
Load Data 252
Write Data 254
L3 (Victim) Cache 232
SNM(s) 236
WIM(s) 238
BAR 235
PFM 234a
PFM 234n
System Coherence Cmd 270
Prefetch Data 272
Cast-in Data 273
Write Data 274

Figure 2B


280
Master 284
Cache Array 284
286n
286a
290
288
Cache Directory 292
Tag Field 294
State Field 296
Replacement Field 298
297
299
CO buffer 295a
CO buffer 295n
282
Snooper 286

Figure 2C


300
Core Load
302
L2 hit?
Yes
No
304
Read data from L2 cache
306
Send data to processor core
310
L2 eviction
312
L3 hit?
Yes
No
314
Read data from L3 cache
316
Update L3 directory state according to Table III & make entry 2nd class LRU
318
Update L2 directory state according to Table IV
320
Request access authority & data from system coherence manager
322
Update L2 directory state according to coherence response
324
Once L2 victim is evicted, install data in L2 cache
326
End
A
A

Figure 3A


Demand memory accesses 338
Trailing PF requests 334
Leading PF requests 330
PF Data 336
PF Data 332
L1 Cache 204
L2 Cache 230
L3 Cache 232
200
System 328
Time

Figure 3B


340
Leading Prefetch
342
L2 hit?
Yes
No
344
L3 hit?
Yes
No
345
PFM initiates L3 eviction
346
PFM requests access authority & data from system coherence manager
347
Update L3 directory state according to coherence response & make entry 1st class MRU
348
Once L3 victim is evicted, install data in L3 cache
349
End

Figure 3C


350
Trailing Prefetch for Load or L/S PF Stream
352
L2 hit?
Yes
No
354
Read data from L2 cache
356
Send data to processor core
360
L2 eviction
362
L3 hit?
Yes
No
364
Read data from L3 cache
363
Collision?
Yes
No
365
Resolved?
Yes
No
366
Update L3 directory state according to Table III & make entry 2nd class LRU
368
Update L2 directory state according to Table IV
370
Request access authority & data from system coherence manager
372
Update L2 directory state according to coherence response
374
Once L2 victim is evicted, install data in L2 cache
376
End
A
A

Figure 3D


380
Trailing Prefetch for Store PF Stream
381
L2 hit?
Yes
No
382
L2 eviction
383
L3 hit?
Yes
No
384
Read data from L3 cache
385
Update L3 directory state according to Table III & make entry 2nd class LRU
386
Update L2 directory state according to Table IV
387
Collision?
Yes
No
388
Resolved?
Yes
No
389
Request access authority & data from system coherence manager
390
Update L2 directory state according to coherence response
391
Once L2 victim is evicted, install data in L2 cache
392
End

Figure 3E


400
Core Store
402
L2 hit?
Yes
No
404
Read data from L2 cache
410
L2 eviction
420
L3 hit?
Yes
No
422
Read data from L3 cache
424
Request access authority & data from system coherence manager
B
426
Update L2 directory state according to coherence response
406
L2 or L3 is HPC?
Yes
No
408
Attempt to claim coherence ownership
410
Granted ?
No
B
Yes
412
Perform coherence cleanup, if needed
414
Update L3 directory state according to Table V & make entry 2nd class LRU
416
Update L2 directory state according to Table VI
430
Merge store with data
432
Once L2 victim is evicted, install data in L2 cache
434
End

Figure 4


L2 Eviction
502
Select victim with replacement policy
504
L2 cache 230
L3 cache 232
500
Time
Need CO?
506
Yes
508
Send cast-in cmd to L3
No
510
Buffer done
Indicate victim storage evacuated
512
Evacuation done
514
Read L3 directory state
520
L3 hit?
522
Yes
Yes
524
Move done
No
526
L3 eviction
Send L3 status to L2
528
530
Update L3 directory state according to Table VII & make 1st class MRU
Dir done
532
Buffer done
540
Read victim from L2 into CO buffer
542
Indicate victim evacuated
544
Send data ready to L3
550
Evacuation done
546
Initiate data move from CO buffer
552
Move data from CO buffer to L3
554
Retire CO buffer
556
Stream data into L3 storage location indicated by CO buffer ID
560
Buffer done
558
Move done
562

Figure 5


L3 Eviction
600
Select victim with replacement policy
602
Perform LCO?
603
Yes
C
No
Perform CO?
604
Yes
No
Buffer done
610
Read L3 victim to castout (CO) buffer
606
Indicate victim storage evacuated
612
Evacuation done
614
Send CO command to snoopers via interconnect
616
D
Wait for random backoff time
624
Wait for CRESP
620
Success?
622
No
Yes
Need to send data?
626
Yes
Send data to destination
628
No
Retire CO buffer
630
Buffer done
632

Figure 6A


C
Read L3 victim to castout (CO) buffer
640
Indicate victim storage evacuated
642
Evacuation done
644
Select target for LCO
646
Send LCO command to snoopers via interconnect
648
Wait for CRESP
650
Success?
652
No
Reached abort threshold?
654
No
Wait for random backoff time
656
Yes
Perform CO?
658
Yes
D
No
Buffer done
660
Yes
Need to send data?
670
Send data to destination
672
No
Retire CO buffer
674
Buffer done
676

Figure 6B


700
Select Victim
710
Generate 1st class mask
712
Inline MRU update
714
Generate 2nd class LRU vector
720
Generate 2nd class mask
722
Inline MRU update
724
Generate 1st class LRU vector
730
Determine if any 2nd class
732
Determine if any 1st class
740
Generate overall LRU mask
742
Inline MRU update
744
Generate overall LRU+1 vector
750
Yes
No
752
Yes
No
0b0..0
754
Yes
No
760
Victim vector
762
Demote vector

Figure 7A


780
Select LCO target
782
Random targeting enabled?
No
Yes
784
Determine home processing node containing home system memory
786
Randomly select target L3 cache within home processing node
788
Select an L3 cache of home processing node that is architecturally close to home system memory as target L3 cache
790
End

Figure 7B


800
CO command to snoopers
802
Snooper is MC?
Yes
No
804
PRESP = Null
806
Address maps to this MC?
Yes
No
808
PRESP = Null
810
Resource available?
Yes
No
812
PRESP = Retry
814
Address collision?
Yes
No
816
PRESP = Retry
818
Allocate resource(s) for CO command
820
PRESP = Ack
822
Wait for CRESP
824
Success?
Yes
No
826
Retire resource
828
End
830
Need to receive data?
Yes
No
832
Wait for data
834
Write control information and data, if any, to memory

Figure 8


900
Begin
902
Log PRESP and wait until all PRESPs logged
904
Any retry?
Yes
906
CRESP = Retry
No
908
Any Ack?
Yes
910
CRESP = Success
No
912
At system scope?
Yes
914
Error
No
916
CRESP = Retry Global

Figure 9



Figure 10A

Figure 10B


LCO Tx/SI Cmd to snoopers
1050
Snooper is L3?
1052
No
1054
PRESP = NULL
Yes
Address collision?
1056
Yes
1058
PRESP = RETRY
No
Tx or SI copy in this L3?
1060
Yes
SNM available ?
1062
Yes
PRESP = TXSL
1066
Allocate SNM for LCO Cmd
1068
No
PRESP = RETRY
1064
This L3 is target ?
1076
Yes
S copy in this L3?
1080
Yes
SNM available ?
1082
Yes
PRESP = SHARED
1084
Allocate SNM for LCO Cmd
1086
Wait for CRESP
1088
CRESP = Target Merge ?
1090
Yes
Update L3 directory according to Table IX & mark MRU
1070
No
PRESP = NULL
1078
No
No
E
Deallocate SNM
1072
End
1074

Figure 10C


E
SI LCO hits lg?
1069
Yes
No
WIM avail?
1071
No
Yes
PRESP = RETRY
1073
PRESP = ACK
1075
Allocate WIM for LCO cmd
1077
Wait for CRESP
1079
CRESP = Target Move?
1081
Yes
No
L3 eviction
1083
Update L3 directory state according to Table VIII, perform demotion, & make entry 2nd class MRU
1085
Wait for data
1087
Once L3 victim is evicted, install data in L3 cache
1089
Deallocate WIM
1091
End
1093

Figure 10D


1100
Begin
1102
Log PRESP & wait until all PRESPs logged
No
1108
Any TXSL?
Yes
1110
CRESP = Success: Early Merge
No
1112
Any Shared?
Yes
1114
CRESP = Success: Target Merge
No
1116
Any Ack?
Yes
1118
CRESP = Success: Target Move
No
1120
Any Retry?
Yes
1124
CRESP = Retry
No
1122
Error

Figure 11

VICTIM CACHE LATERAL CASTOUT TARGETING

This invention was made with United States Government support under Agreement No. HR0011-07-9-0002 awarded by DARPA. THE GOVERNMENT HAS CERTAIN RIGHTS IN THE INVENTION.

BACKGROUND OF THE INVENTION

1. Technical Field

The present invention relates in general to data processing and more particularly to data caching in data processing system.

2. Description of the Related Art

A conventional symmetric multiprocessor (SMP) computer system, such as a server computer system, includes multiple processing units all coupled to a system interconnect, which typically comprises one or more address, data and control buses. Coupled to the system interconnect is a system memory, which represents the lowest level of volatile memory in the multiprocessor computer system and generally is accessible for read and write access by all processing units. In order to reduce access latency to instructions and data residing in the system memory, each processing unit is typically further supported by a respective multi-level cache hierarchy, the lower level(s) of which may be shared by one or more processor cores.

Because multiple processor cores may request write access to a same cache line of data and because modified cache lines are not immediately synchronized with system memory, the cache hierarchies of multiprocessor computer systems typically implement a cache coherency protocol to ensure at least a minimum level of coherence among the various processor core's "views" of the contents of system memory. In particular, cache coherency requires, at a minimum, that after a processing unit accesses a copy of a memory block and subsequently accesses an updated copy of the memory block, the processing unit cannot again access the old copy of the memory block.

A cache coherency protocol typically defines a set of cache states stored in association with the cache lines stored at each level of the cache hierarchy, as well as a set of coherency messages utilized to communicate the cache state information between cache hierarchies. In a typical implementation, the cache state information takes the form of the well-known MESI (Modified, Exclusive, Shared, Invalid) protocol or a variant thereof, and the coherency messages indicate a protocol-defined coherency state transition in the cache hierarchy of the requestor and/or the recipients of a memory access request. The MESI protocol allows a cache line of data to be tagged with one of four states: "M" (Modified), "E" (Exclusive), "S" (Shared), or "I" (Invalid). The Modified state indicates that a memory block is valid only in the cache holding the Modified memory block and that the memory block is not consistent with system memory. When a coherency granule is indicated as Exclusive, then, of all caches at that level of the memory hierarchy, only that cache holds the memory block. The data of the Exclusive memory block is consistent with that of the corresponding location in system memory, however. If a memory block is marked as Shared in a cache directory, the memory block is resident in the associated cache and in at least one other cache at the same level of the memory hierarchy, and all of the copies of the coherency granule are consistent with system memory. Finally, the Invalid state indicates that the data and address tag associated with a coherency granule are both invalid.

The state to which each memory block (e.g., cache line or sector) is set is dependent upon both a previous state of the data within the cache line and the type of memory access request received from a requesting device (e.g., the processor). Accordingly, maintaining memory coherency in the system requires that the processors communicate messages via the system interconnect indicating their intention to read or write memory locations. For example, when a processor desires to write data to a memory location, the processor may first inform all other processing elements of its intention to write data to the memory location and receive permission from all other processing elements to carry out the write operation. The permission messages received by the requesting processor indicate that all other cached copies of the contents of the memory location have been invalidated, thereby guaranteeing that the other processors will not access their stale local data.

In some systems, the cache hierarchy includes multiple levels, with each lower level generally having a successively longer access latency. Thus, a level one (L1) cache generally has a lower access latency than a level two (L2) cache, which in turn has a lower access latency than a level three (L3) cache.

The level one (L1) or upper-level cache is usually a private cache associated with a particular processor core in an MP system. Because of the low access latencies of L1 caches, a processor core first attempts to service memory access requests in its L1 cache. If the requested data is not present in the L1 cache or is not associated with a coherency state permitting the memory access request to be serviced without further communication, the processor core then transmits the memory access request to one or more lower-level caches (e.g., level two (L2) or level three (L3) caches) for the requested data.

Typically, when a congruence class of an upper-level cache becomes full, cache lines are removed ("evicted") and may be written to a lower-level cache or to system memory for storage. In some cases, a lower level cache (e.g., an L3 cache) is configured as a "victim" cache, which conventionally means that the lower level cache is entirely populated with cache lines evicted from one or more higher level caches in the cache hierarchy rather than by memory blocks retrieved by an associated processor. Conventional victim caches generally are exclusive, meaning that a given memory block does not reside in a higher level cache and its associated victim cache simultaneously.

SUMMARY OF THE INVENTION

In one embodiment, a data processing system includes a plurality of processing units coupled by an interconnect fabric. In response to a data request, a victim cache line is selected for castout from a first lower level cache of a first processing unit, and a target lower level cache of one of the plurality of processing units is selected based upon architectural proximity of the target lower level cache to a home system memory to which the address of the victim cache line is assigned. The first processing unit issues on the interconnect fabric a lateral castout (LCO) command that identifies the victim cache line to be castout from the first lower level cache and indicates that the target lower level cache is an intended destination. In response to a coherence response indicating success of the LCO command, the victim cache line is removed from the first lower level cache and held in the second lower level cache.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is high level block diagram of an exemplary data processing system in accordance with the present invention;

FIG. **2**A is a high level block diagram of a processing unit from FIG. **1**;

FIG. **2**B is a more detailed block diagram of an exemplary embodiment of a processor core and associated cache hierarchy from FIG. **2**A;

FIG. **2**C is an exemplary embodiment of a cache memory from FIG. **2**B;

FIG. **3**A is a high level logical flowchart of an exemplary method of performing a processor load in accordance with one embodiment;

FIG. **3**B is a time-space diagram of a sequence of leading and trailing prefetches in accordance with one embodiment;

FIG. **3**C is a high level logical flowchart of an exemplary method of performing a leading prefetch in accordance with one embodiment;

FIG. **3**D is a high level logical flowchart of an exemplary method of performing a trailing prefetch for a load or load/store prefetch stream in accordance with one embodiment;

FIG. **3**E is a high level logical flowchart of an exemplary method of performing a trailing prefetch for a store prefetch stream in accordance with one embodiment;

FIG. **4** is a high level logical flowchart of an exemplary method of performing a processor store in accordance with one embodiment;

FIG. **5** is a high level flowchart of an exemplary process for performing an L2 eviction and L3 cast-in in accordance with one embodiment.

FIGS. **6**A-**6**B together form a high level logical flowchart of an L3 eviction in accordance with one embodiment;

FIG. **7**A is a high level logical flow diagram of an exemplary process for selecting a victim cache line for eviction from an L3 cache;

FIG. **7**B is a high level logical flowchart of an exemplary process of selecting a target of a lateral castout (LCO) in accordance with one embodiment;

FIG. **8** is a high level logical flowchart of an exemplary process by which a snooper handles a castout (CO) command in accordance with one embodiment;

FIG. **9** is a high level logical flowchart of the processing of the coherence responses of a castout (CO) command in accordance with one embodiment;

FIG. **10**A is a high level logical flowchart of an exemplary process by which a snooper handles a lateral castout (LCO) command in accordance with one embodiment;

FIG. **10**B is a high level logical flowchart of an exemplary process by which a snooper handles a lateral castout (LCO) of a modified cache line in accordance with one embodiment;

FIGS. **10**C-**10**D together form a high level logical flowchart of an exemplary process by which a snooper handles a lateral castout (LCO) of a possibly shared cache line in accordance with one embodiment; and

FIG. **11** is a high level logical flowchart of the processing of the coherence responses of a lateral castout (LCO) command in accordance with one embodiment.

DETAILED DESCRIPTION OF ILLUSTRATIVE EMBODIMENT

With reference now to the figures and, in particular, with reference to FIG. **1**, there is illustrated a high level block diagram of an exemplary embodiment of a multiprocessor data processing system in accordance with the present invention. As shown, data processing system **100** includes multiple processing nodes **102***a*, **102***b* for processing data and instructions. Processing nodes **102***a*, **102***b* are coupled to a system interconnect **110** for conveying address, data and control information. System interconnect **110** may be implemented, for example, as a bused interconnect, a switched interconnect or a hybrid interconnect.

In the depicted embodiment, each processing node **102** is realized as a multi-chip module (MCM) containing four processing units **104***a*-**104***d*, each preferably realized as a respective integrated circuit. The processing units **104***a*-**104***d* within each processing node **102** are coupled for communication by a local interconnect **114**, which, like system interconnect **110**, may be implemented with one or more buses and/or switches. Local interconnects **114** and system interconnect **110** together form an interconnect fabric, which preferably supports concurrent communication of operations of differing broadcast scopes. For example, the interconnect fabric preferably supports concurrent communication of operations limited in scope to a single processing node **102** and operations broadcast to multiple processing nodes **102**.

The devices coupled to each local interconnect **114** include not only processing units **104**, but also one or more system memories **108***a*-**108***d* (e.g., formed of dynamic random access memory (DRAM), static RAM (SRAM), flash memory or other memory technology), which collectively represent the lowest level of data storage in data processing system **100** addressable via real addressing. Data and instructions residing in system memories **108** can generally be accessed and modified via real addresses by a processor core (FIG. **2**A) in any processing unit **104** in any processing node **102** of data processing system **100**. In alternative embodiments of the invention, one or more system memories **108** can be coupled to system interconnect **110** rather than a local interconnect **114**.

Those skilled in the art will appreciate that data processing system **100** can include many additional unillustrated components, such as peripheral devices, interconnect bridges, non-volatile storage, ports for connection to networks or attached devices, etc. Because such additional components are not necessary for an understanding of the present invention, they are not illustrated in FIG. **1** or discussed further herein. It should also be understood, however, that the enhancements provided by the present invention are applicable to data processing systems of diverse architectures and are in no way limited to the generalized data processing system architecture illustrated in FIG. **1**.

Referring now to FIG. **2**A, there is depicted a more detailed block diagram of an exemplary processing unit **104** in accordance with the present invention. In the depicted embodiment, each processing unit **104** includes multiple instances of a processor core and associated cache hierarchy, which are collectively identified by reference numeral **200**. In the depicted embodiment, each processing unit **104** also includes an integrated memory controller (IMC) **206** that controls read and write access to one or more of the system memories **108***a*-**108***d* within its processing node **102** in response to requests received from processor cores and operations snooped on the local interconnect **114**.

Still referring to FIG. **2**A, each processing unit **104** also includes an instance of coherence management logic **210**, which implements a portion of the distributed snoop-based coherency signaling mechanism that maintains cache coherency within data processing system **100**. In addition, each processing unit **104** includes an instance of forwarding logic **212** for selectively forwarding communications between its local interconnect **114** and system interconnect **110**. Finally, each processing unit **104** includes an integrated I/O (input/output) controller **214** supporting the attachment of one or more I/O devices, such as I/O device **216**. I/O controller **214**

may issue operations on local interconnect **114** and/or system interconnect **110** in response to requests by I/O device **216**.

With reference now to FIG. **2**B is a more detailed block diagram of an exemplary embodiment of a processor core and associated cache hierarchy **200** from FIG. **2**A. Processor core **202** includes circuitry for processing instructions and data. In the course of such processing, the circuitry of processor core **202** generates various memory access requests, such as load and store requests.

The operation of processor core **202** is supported by a cache memory hierarchy including a store-through level one (L1) cache **204** within each processor core **202**, a store-in level two (L2) cache **230**, and a lookaside L3 cache **232** that is utilized as a victim cache for L2 cache **230** and accordingly is filled by cache lines evicted from L2 cache **230**. In contrast to many conventional victim cache arrangements, the contents of L3 cache **232** are not exclusive of the contents of L2 cache **230**, meaning that a given memory block may be held concurrently in L2 cache **230** and L3 cache **232**.

In at least some embodiments, processor core **202** further includes a streaming prefetcher **203** that generates and transmits to the memory hierarchy prefetch requests requesting data to be staged into its cache memory hierarchy in advance of need (e.g., prior to a demand load or store). In preferred embodiments, streaming prefetcher **203** supports multiple concurrent prefetching streams, and in at least some cases, supports multiple concurrent prefetching stream types having differing behaviors. For example, in one exemplary embodiment, streaming prefetcher **203** includes a load prefetch stream to prefetch memory blocks that may be the target of load requests, a store prefetch stream to prefetch memory blocks that may be targets of store requests, and a load/store prefetch stream to prefetch memory blocks that may be target of load and/or store requests. These different prefetch streams may have different associated strides, stream depths, caching rules, etc., as discussed further below. In other embodiments, processor core **202** may implement prefetching without streaming, that is, without fetching from a sequence of addresses linked by a common stride.

In order to support prefetching while limiting the associated cost and latency impact on the cache memory hierarchy, L3 cache **232** includes at least one and preferably many prefetch machines (PFMs) **234***a*-**234***n* that, in response to prefetch requests issued by streaming prefetcher **203** that miss in the cache memory hierarchy, manage the transmission of the prefetch requests to the system for service and the installation of prefetch data in the cache memory hierarchy, as discussed further below with reference to FIGS. **3**B-**3**E. In one embodiment, prefetch machines **234***a*-**234***n* can be implemented within master **284** (see FIG. **3**) as special-purpose prefetch machines dedicated to handling prefetch requests, as disclosed in greater detail in U.S. patent application Ser. No. 11/45,333, which was filed Jul. 13, 2006, and is incorporated herein by reference in its entirety.

L3 cache **232** further includes at least one and preferably a plurality of snoop machines (SNM(s)) **236** and at least one and preferably a plurality of write inject machine(s) (WIM(s)) **238** within snooper **286** (see FIG. **3**). As discussed further below, SNM(s) **236** and WIM(s) **238** handle the cast-in of cache lines into L3 cache **232** in response to lateral castout (LCO) commands received from other L3 caches **232**. In the described embodiment, SNM(s) **236** are used to handle cast-ins that require no data movement and thus preferably do not include the inbound data management constructs, while WIM(s) **238** are employed to handle LCO commands requiring data movement and accordingly include inbound data management constructs (making them more costly than SNM(s) **236**). L3 cache **232** also includes a base address register (BAR) facility **235** that is programmed (e.g., during system initialization) to indicate the system memory **108** (referred to herein as the 'home system memory") to which each range of real addresses in the real address space utilized by the volatile memory of data processing system **100** is assigned. In a preferred embodiment, BAR facility **235** additionally indicates which processing node **102** contains the home system memory **108** and the processing unit **104** containing the IMC **206** for the home system memory **108**.

FIG. **2**B also illustrates an exemplary flow of requests, data and coherence communication within the cache memory hierarchy of processor core **202**. In the depicted arrangement, dashed lines represent the flow of requests and coherence commands, and solid lines represent data flow.

As shown, processor core **202** transmits load requests **240** to, and receives load data **242** from L2 cache **230**. Processor core **202** also transmits store requests **244** and associated store data **246** to gathering logic **248**, which gathers the store data associated with multiple requests into one cache line of data and transmits the gathered store data **249** to L2 cache **230** in conjunction with one gathered store request **247**. Although illustrated separately for clarity, gathering logic **248** may be incorporated within processor core **202** and/or L2 cache **230**.

L2 cache **230** transmits system coherence commands **250** to coherence management logic **210** of FIG. **2**A for compilation and/or transmission on the interconnect fabric. L2 cache **230** also transmits write data **254** to, and receives load data **252** from IMC **206** and/or interconnect logic **212**. L2 cache **230** may also request load data from L3 cache **232** via a load request **260** and receive load data **262** from L3 cache **232**. To remove a cache line from L2 cache **230**, L2 cache **230** may issue a cast-in request to L3 cache **232**, which in turn receives the cache line as cast-in data **266**. Similar to L2 cache **230**, L3 cache **232** may interact with IMCs **206** and/or cache memories in other cache hierarchies by issuing system coherence commands **270**, receiving prefetch data **272** and/or cast-in data **273**, and/or transmitting write data **274**.

Although the illustrated cache hierarchy includes only three levels of cache, those skilled in the art will appreciate that alternative embodiments may include additional levels (L4, L5, etc.) of on-chip or off-chip in-line or lookaside cache, which may be fully inclusive, partially inclusive, or non-inclusive of the contents the upper levels of cache. Further, any of the various levels of the cache hierarchy may be private to a particular processor core **202** or shared by multiple processor cores **202**. For example, in some implementations, the cache hierarchy includes an L2 cache **230** for each processor core **202**, with multiple of the L2 caches **230** sharing a common L3 victim cache **232**.

Referring now to FIG. **2**C, there is depicted an exemplary embodiment of a cache memory **280** that may be utilized to implement L2 cache **230** or L3 cache **232** from FIG. **2**B. As shown, cache memory **280** includes an array and directory **282**, as well as a cache controller comprising a master **284** and a snooper **286**. Snooper **286** snoops operations from local interconnect **114**, provides appropriate responses, and performs any accesses to array and directory **282** required by the operations. Master **284** initiates transactions on local interconnect **114** and system interconnect **110** and accesses array and directory **282** in response to memory access (and other) requests originating within the processor core and cache hierarchy **200**. In at least some embodiments, master **284** also handles casting out data to lower levels of the memory hierarchy (e.g., L3 victim cache **232** or system memory **108**).

Array and directory **282** includes a set associative cache array **284** including multiple ways **286***a*-**286***n*. Each way **286**

includes multiple entries **288**, which in the depicted embodiment each provide temporary storage for up to a full memory block of data, e.g., 128 bytes. Each cache line or memory block of data is logically formed of multiple sub-blocks **290** (in this example, four sub-blocks of 32 bytes each) that may correspond in size, for example, to the smallest allowable access to system memories **108***a*-**108***d*. In at least some embodiments, sub-blocks **290** may be individually accessed and cached in cache array **284**.

Array and directory **282** also includes a cache directory **292** of the contents of cache array **284**. As in conventional set associative caches, memory locations in system memories **108** are mapped to particular congruence classes within cache arrays **284** utilizing predetermined index bits within the system memory (real) addresses. The particular cache lines stored within cache array **284** are recorded in cache directory **292**. As understood by those skilled in the art, directory entries in cache directory **292** comprise at least tag fields **294**, which specify the particular cache line, if any, stored in each entry of cache array **284** utilizing a tag portion of the corresponding real address, state fields **296**, which indicate the coherence states (also referred to as cache states) of the entries of cache array **284**, and replacement fields **298**.

In the depicted embodiment, each replacement field **298** includes a chronology vector **297** indicating an access chronology (or rank) of the associated cache line with respect to all other cache lines belonging to the same congruence class. In addition, in the depicted embodiment, replacement fields **298** of at least L3 caches **232** include a class subfield **299** indentifying to which of multiple classes each of the cache lines of the congruence class belongs. For example, if two classes are implemented, class membership can be indicated in an encoded format by a single bit for each cache line in the congruence class. (Of course, other encodings of class subfield **299** are possible.) As described further below, the classes of cache lines are utilized when selecting victim cache lines for eviction so that cache lines more likely to be accessed by the associated processor core **202** are preferentially retained in cache array **284**. For example, in an embodiment in which two classes are implemented (as assumed hereafter), the first class can be used to designate cache lines more likely to be accessed from the cache by the associated processor core **202**, and the second class can be used to designate cache lines less likely to be accessed from the cache by the associated processor core **202**.

Although the exemplary embodiment illustrates that each state field **296** provides state information for a respective associated cache line in cache array **284**, those skilled in the art will appreciate that in alternative embodiments a cache directory **292** can include a respective state field for each sub-block **290**. Regardless of which implementation is selected, the quantum of data associated with a coherence state is referred to herein as a coherence granule.

To support the transfer of castout cache lines, array and directory **282** includes at least one and preferably multiple castout (CO) buffers **295***a*-**295***n*, which are each preferably identified with a unique respective CO buffer ID. While a CO buffer **295** is allocated to master **284** for a castout operation, the CO buffer **295** has a "busy" state, and when the CO buffer is released or deallocated by master **284**, then the CO **295** buffer has a "done" state.

In a preferred embodiment, data processing system **100** maintains coherency with a non-blocking, broadcast-based coherence protocol that utilizes a set of predefined coherence states in state fields **296** and a robust set of associated request, response, and notification types. Coherence requests are broadcast with a selected scope to cache memories, as well as IMCs **206** and I/O controllers **214**. As discussed further below, the selected scope of broadcast can be "global", that is, inclusive of all participants (e.g., IMCs **206**, IOCs **214**, L2 caches **230** and L3 caches **232**) in data processing system **100** or have a more restricted scope excluding at least some participants. In response to snooping the coherence requests, the participants provide partial responses (PRESPs), which are aggregated (preferably at coherence management logic **210** of the requesting processing unit **104**) to form the basis for a coherence transfer decision. Notification of the decision is subsequently broadcast to the participants in a combined response (CRESP) indicating the final action to be taken. Thus, the coherence protocol employs distributed management.

In a preferred embodiment, global and local (or scope-limited) broadcast transport mechanisms are both integrated. Thus, a given request can be broadcast globally or locally, where a local scope may correspond, for example, to a single processing node **102**. If all information necessary to resolve a coherence request exists within the local broadcast scope, then no global broadcast is necessary. If a determination cannot be made that all information necessary to resolve the coherence request is present within the local broadcast scope, the coherence request is broadcast globally (or at least with an increased scope including at least one additional participant).

To ensure a reasonable likelihood of a successful local resolution of coherence requests, a mechanism indicative of the distribution of cached copies of memory blocks within the cache hierarchies is useful. In a preferred embodiment, the mechanism includes inclusion of a scope-state indication per memory block (e.g., 128 bytes) in system memory **108** and an appropriate set of coherence states for state fields **296** in L2 and L3 caches **230**, **232**. In one embodiment, the scope-state indication for each memory block is a single bit integrated into the redundant content for error correction stored in system memory **108**. For each memory block, the scope-state indicator indicates whether the memory block might be in use outside of the local scope where the system memory **108** resides. Since the scope-state indicator is stored with the data bits, the scope-state bit is automatically read or written whenever the data is read or written.

Coherence states that may be utilized in state field **296** to indicate state information may include those set forth in Table I below. Table I lists the name of various coherence states in association with a description of the state, an indication of the authority conveyed by the coherence state to read and/or update (which includes the authority to read) the associated cache line, an indication of whether the coherence state permits other cache hierarchies to concurrent hold the associated cache line, an indication of whether the associated cache line is castout upon deallocation, and an indication of if and when the associated cache line is to be sourced in response to snooping a request for the cache line. A further description of the implementation of at least some of these coherence states is described in detail in U.S. patent application Ser. No. 11/055,305, which is incorporated herein by reference.

TABLE I

State	Description	Authority	Sharers	Data Castout	Source data
I	Invalid	None	N/A	N/A	N/A
Id	Deleted, do not allocate	None	N/A	N/A	N/A
Ig	Invalid, cached scope-state	None	N/A	N/A	N/A

TABLE I-continued

State	Description	Authority	Sharers	Data Castout	Source data
In	Invalid, scope predictor	None	N/A	N/A	N/A
S	Shared	Read	Yes	No	No
Sl	Shared, local data source	Read	Yes	No	At request
T	Formerly MU, now shared	Update	Yes	Yes	At CRESP
Te	Formerly ME, now shared	Update	Yes	No	At CRESP
Tn	Formerly MU, now shared	Update	Yes	Yes	At CRESP
Ten	Formerly ME, now shared	Update	Yes	No	At CRESP
M	Modified, avoid sharing	Update	No	Yes	At request
Me	Exclusive	Update	No	No	At request
Mu	Modified, bias toward sharing	Update	No	Yes	At request

As shown in Table II below, a number of the coherence states set forth in Table I provide low-latency access to high-usage scope states while protecting system memories **108** from increased traffic due to scope-state queries and updates. Note that when a cached scope state is deallocated, it is typically cast out (i.e., written back) to memory. For cases in which the implied scope state might be global, the castout is functionally required to ensure that coherence is maintained. For cases in which the implied scope state is known to be local, the castout is optional, as it is desirable but not necessary to localize the broadcast scope for subsequent operations.

TABLE II

State	Implied scope state	Scope-state castout
I	None	None
Id	None	None
Ig	Existing copies probably global	Required, global
In	Existing copies probably local	None
S	Unknown	None
Sl	Unknown	None
T	Shared copies probably global	Required, global
Te	Shared copies probably global	Required, global
Tn	Shared copies all local	Optional, local
Ten	Shared copies all local	None
M	Local	Optional, local
Me	Local	None
Mu	Local	Optional, local

The combination of the scope-state bits in system memory **108** and the coherence states described herein provides a low-cost alternative to a directory-based approach and integrates cleanly into the non-blocking, broadcast-based distributed coherence protocol. Because some workloads localize well and others do not, processing unit **104** may also incorporate a number of predictors to determine whether a given coherence request should be initially broadcast with a local scope or should be broadcast globally immediately. For workloads that exhibit a high degree of processor-to-memory localization, and for workloads that have varying mixtures of locally resolvable traffic, laboratory results show that scope-limited speculative snoop resolution is highly effective.

With reference now to FIG. **3**A, there is illustrated a high level logical flowchart of an exemplary method of performing a load of a processor core in accordance with one embodiment. The illustrated process begins at block **300** in response to receipt by L2 cache **230** of a load request **240** from its associated processor core **202** following a miss in the L1 cache **204**. In response to the load request **240**, master **284** of L2 cache **230** accesses its cache directory **292** to determine whether or not the target address specified by load request **240** hits in cache directory **292** (block **302**). If so, the process then proceeds to blocks **304** and **306**, which depict master **284** of L2 cache **230** reading the requested cache line of data from its cache array **284** and then sending the cache line of data to the requesting processor core **202**. Thereafter, the process terminates at block **326**.

Returning to block **302**, in response to an L2 miss, the process proceeds to block **310**, which illustrates L2 cache **230** selecting and initiating eviction of a victim cache line, as discussed further below with reference to FIGS. **5-6**. In addition, L2 cache **230** transmits the load request to L3 cache **232** as a load request **260**. Consequently, master **284** of L3 cache **232** accesses its cache directory **292** to determine whether or not the target address specified by load request **260** hits in cache directory **292** of L3 cache **232** (block **312**). If not, the process passes to block **320**, which is described below. If, however, load request **260** hits in cache directory **292** of L3 cache **232**, the process proceeds to block **314**, which depict master **284** of L3 cache **232** reading the requested cache line of data from cache array **284** of L3 cache **232** and providing the requested cache line to L2 cache **230**. The process then bifurcates and proceeds to blocks **306** and **316**.

As noted above, block **306** depicts L3 cache **232** sending the requested cache line of data to the requesting processor core **202**. Thereafter, the first branch of the process ends at block **326**. Block **316** illustrates master **284** of L3 cache **232** updating the coherence state of the requested cache line of data in cache directory **292** of L3 cache **232** in accordance with Table III, below.

TABLE III

	Final L3 State						
Initial L3 State	Load	Ifetch	Xlate	Prefetch (Load)	Load (Lock)	Prefetch (Store)	Prefetch (Ld/St)
M	SL	SL	SL	SL	I	I	I
Mu	SL	SL	SL	SL	I	I	I
Me	SL	SL	SL	SL	I	I	I
T	S	S	S	S	S	S	S
Te	S	S	S	S	S	S	S
Tn	S	S	S	S	S	S	S
Ten	S	S	S	S	S	S	S
SL	S	S	S	S	S	S	S
S	S	S	S	S	S	S	S
Ig	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)
In	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)
I	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)

In contrast with conventional implementations in which any fetch that hit in an L3 victim cache in a data-valid coherency state (e.g., M, Mu, Me, T, Te, Tn, Ten, S1 or S) resulted in the invalidation of the matching cache line in the L3 directory, Table III discloses that a fetch hit in the Tx or Sx states (where the "x" refers to any variant of the base coherence state) preserves the matching cache line in L3 cache **232** in the S state. In this way, the likelihood of a castout hit in L3 cache **232** is increased, which as discussed further below, reduces data movement and thus power dissipation in the event of an L2 eviction.

As further indicated at block **316**, in each case in which an update to cache directory **292** is made, the class of the matching cache line in L3 cache **232** is set to (or retained as) second class in class subfield **299**. As indicated above, the designation of the matching cache line as second class indicates that

the matching cache line is not likely to be accessed from L3 cache **232** by the associated processor core **202**, in the case of block **316** because the matching cache line already resides at a higher level of the cache hierarchy. Consequently, the matching cache line will be preferred in the selection of a victim cache line for eviction from L3 cache **232** relative to cache lines belonging to the first class. The preference of the matching cache line as a victim cache line is further enhanced by setting the associated chronology vector **297** to indicate a replacement order or rank for the matching cache line as other than Most Recently Used (MRU), such as LRU or (LRU+1).

Further, for a hit in an Mx (e.g., M, Mu or Me) state, the coherency state is updated to either SL or I, depending upon the type of memory access requested. For core loads, as depicted in FIG. **3**A, as well as for instruction fetches (Ifetch), fetches of page table entries containing information utilized for address translation (Xlate), and prefetches for load prefetch streams, the matching entry is preferably updated with a coherency state of SL and a replacement order other than Most Recently Used (e.g., LRU or LRU−1). Atomic loads, prefetches generated within a store prefetch stream and prefetches generated within a load/store prefetch stream preferably cause the matching entry is to be invalidated (i.e., set to I). The distinction in the final L3 cache states is made based upon different expectations as to whether a store to the memory block will subsequently be made. For instruction fetches, fetches of page table entries, and prefetches for load prefetch streams, no store operation is likely. Thus, it is helpful if the target memory block is retained in L3 cache **232**. However, for atomic loads, prefetches generated within a store prefetch stream and prefetches generated within a load/store prefetch stream, a subsequent store to the target memory block is extremely likely, and leaving a copy of the memory block in L3 cache **232** would require a background kill bus operation to invalidate the L3 copy when a subsequent store to the memory block is made. The additional background kill bus operation would not only dissipate additional power, but also prolong the duration of the store operation must be managed by master **284** of L2 **230**.

As illustrated at block **318**, master **284** of L2 cache **230** also updates the state of the requested cache line of data in cache directory **292** of L2 cache **230** in accordance with Table IV, below. In the depicted exemplary embodiment, the coherency state is updated in cache directory **292** of L2 cache **230** to the initial state of the cache line in L3 cache **232** if the initial coherence state of the target memory block in cache directory **292** of L3 cache **232** is other than Mx (e.g., M, Mu or Me). For core loads, as depicted in FIG. **3**A, as well as for instruction fetches (Ifetch), fetches of page table entries containing information utilized to perform address translation (Xlate), and prefetches for load prefetch streams, the matching entry is preferably updated in L2 cache **230** to Tn if the initial state in L3 cache **232** is M or Mu, and is updated to Ten in L2 cache **230** if the initial state in L3 cache **232** is Me. An L2 coherence state with less authority than the initial L3 coherence state is employed for these types of memory access requests because of the low likelihood of a subsequent store and the desire to avoid data movement in the event of a subsequent L2 castout. However, it is preferable if L2 cache **230** is updated to the initial coherence state in L3 cache **232** if the requested memory access is an atomic load, prefetch generated within a store prefetch stream, or prefetch generated within a load/store prefetch stream that hits in L3 cache **232** in an Mx coherence state because of the high likelihood that these operations will be followed by a store operation.

TABLE IV

	Final L2 State						
Initial L3 State	Load	Ifetch	Xlate	Prefetch (load)	Load (Lock)	Prefetch (Store)	Prefetch (Ld/St)
M	Tn	Tn	Tn	Tn	M	M	M
Mu	Tn	Tn	Tn	Tn	Mu	Mu	Mu
Me	Ten	Ten	Ten	Ten	Me	Me	Me
T	T	T	T	T	T	T	T
Te	Te	Te	Te	Te	Te	Te	Te
Tn	Tn	Tn	Tn	Tn	Tn	Tn	Tn
Ten	Ten	Ten	Ten	Ten	Ten	Ten	Ten
SL	SL	SL	SL	SL	SL	SL	SL
S	S	S	S	S	S	S	S
Ig	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)
In	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)
I	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)	(n/a)

As shown at block **324**, once the victim cache line has been evicted from L2 cache **230**, the cache line of data supplied to processor core **202** is also installed in L2 cache **230** (block **324**). Thereafter, the process terminates at block **326**.

Referring now to block **320**, in response to the load requests **240**, **260** missing in L2 cache **230** and L3 cache **232**, master **284** of L2 cache **230** requests access authority and the target memory block from the system coherence manager (e.g., the distributed coherence management system described above) by transmitting an appropriate command **250** to the local instance of interconnect logic **212**. Master **284** then updates the coherence state for the target memory block in its cache directory **292** in accordance with the coherence response (also referred to as combined response (CRESP)) for its request (block **322**). Master **284** also supplies the target memory block to the requesting processor core, as indicated by the process passing through page connector A to block **306**. In addition, once eviction of the L2 victim is complete and load data **252** is received, master **284** updates cache array **284** with the target memory block (block **324**). Thereafter, the process ends at block **326**.

With reference now to FIG. **3**B, there is depicted a time-space diagram of an exemplary prefetching sequence in accordance with one embodiment. In the diagram, a particular processor core and cache hierarchy **200** is depicted as containing an L1 cache **204**, L2 cache **230** and L3 cache **232**, and the remainder of data processing system **100** is collectively represented as system **328**.

In the depicted exemplary prefetching sequence, a stream of leading prefetch (PF) requests **330** is generated by the streaming prefetcher **203** in the processor core **202** and then passed to the cache memory hierarchy. Thus, in contrast to demand load requests, the leading prefetch requests (as well as other prefetch requests) are not generated through the execution of an ISA instruction by the instruction execution circuitry of processor core **202**, but rather generated by streaming prefetcher **203** in anticipation of execution of one or more ISA instructions that implicitly or explicitly indicate a memory access. Although the leading prefetch requests **330** accesses each level of the cache memory hierarchy, as shown in FIG. **3**B by circles, it is generally the case that the target memory blocks of leading prefetch requests **330** do not initially reside in the cache memory hierarchy. Accordingly, a prefetch machine (PFM) **234** within L3 cache **232** generally issues leading prefetch requests **330** to system **328**, which supplies the target memory blocks of leading prefetch requests as prefetch data **332**. In contrast to conventional prefetching schemes, prefetch data **332** responsive to leading prefetch requests **330** are installed in L3 (victim) cache **232** rather than directly in L2 cache **230**.

In some operating scenarios, for purposes of local optimization, leading prefetch requests **330** are discarded at some level of the cache memory hierarchy and not forwarded to a lower level of the cache memory hierarchy or system **328**. Because leading prefetch requests **330** are speculative in nature and are generated to reduce latency rather than in response to a demand memory access, the discarding of a leading prefetch request will not affect correctness.

Subsequent to a leading prefetch request **330** and nearer in time to an anticipated demand memory access request (e.g., demand load or store request), streaming prefetcher **203** issues a corresponding trailing prefetch request **334** targeting the same target memory block. Although trailing prefetch requests **334** access each level of the cache memory hierarchy, as shown in FIG. **3**B by circles, it is generally the case that the target memory block of a trailing prefetch request **334** initially resides only in L3 cache memory **232** as a result of the earlier corresponding leading prefetch request **330**. Accordingly, L3 cache **232** generally services a trailing prefetch request **334** by supplying the target memory block of the trailing prefetch request to one or more higher levels of cache memory as prefetch data **336**. For example, in an embodiment described below, prefetch data **336** of load or load/store prefetch streams are installed in both L1 cache **204** and L2 cache **230**, while prefetch data **336** of store prefetch streams are installed in L2 cache **230**, but not L1 cache **204**. This distinction is made because in the preferred embodiment, L1 cache **230** is a store-through cache and L2 cache **230** is a store-in cache, meaning that all store requests are resolved at L2 cache **230**.

With the prefetch data staged within the cache memory hierarchy in the manner described above, a demand memory access **338** (e.g., a demand load or store request) subsequent to a leading prefetch request **330** and a trailing prefetch request **334** is serviced with an optimal access latency.

Referring now to FIG. **3**C, there is depicted a high level logical flowchart of an exemplary method of performing a leading prefetch in accordance with one embodiment. The illustrated process begins at block **340** following a miss of leading prefetch request in the L1 cache **204** and then proceeds to block **342**, which depicts a determination by L2 cache **230** whether or not the leading prefetch request hits in cache directory **292** of L2 cache **230**. If so, the leading prefetch request is aborted, and the process terminates at block **349**. If, however, the leading prefetch request misses in L2 cache **230**, the process proceeds to block **344**.

Block **344** depicts a determination by L3 cache **232** whether or not the leading prefetch request hits in cache directory **292** of L3 cache **232**. If so, the leading prefetch request is aborted, and the process terminates at block **349**. If, however, the leading prefetch request misses in L3 cache **232**, the process proceeds to block **345**. Block **345** illustrates L3 cache **232** allocating a prefetch machine **234** to manage the leading prefetch request, which in turn initiates the process of evicting a victim entry from L3 cache **232** in preparation for receiving the prefetch data requested by the leading prefetch request.

Next, at block **346**, the prefetch machine **234** allocated to the leading prefetch request requests access authority and the target memory block from the system coherence manager (e.g., the distributed coherence management system described above) by transmitting an appropriate command **250** to the local instance of interconnect logic **212**. Prefetch machine **234** then updates the coherence state for the target memory block in its cache directory **292** in accordance with the coherence response (also referred to as combined response (CRESP)) for its request and sets the class and rank indicated by the replacement field **298** of the target memory block to first class MRU (block **347**). The designation of the target memory block of the leading prefetch request as first class indicates that the target memory block is likely to again be the target of a memory access request by the associated processor core **202**. In addition, once eviction of the L3 victim entry is complete and prefetch data **332** is received, prefetch machine **234** updates cache array **284** of L3 cache **232** with the target memory block (block **348**). Thereafter, the process ends at block **349**.

With reference now to FIG. **3**D, there is illustrated a high level logical flowchart of an exemplary method of performing a trailing prefetch for a load or load/store prefetch stream in accordance with one embodiment. The process depicted in FIG. **3**D begins at block **350** following a miss of trailing prefetch request of a load or load/store prefetch stream in an L1 cache **204** and then proceeds to block **352**. At block **352**, master **284** of L2 cache **230** accesses its cache directory **292** to determine whether or not the target address specified by the trailing prefetch request hits in cache directory **292** of L2 cache **230**. If so, the process then proceeds to blocks **354** and **356**, which depict master **284** of L2 cache **230** reading the requested cache line of data from its cache array **284** and then sending the target cache line of data to the requesting processor core **202**. Thereafter, the process terminates at block **376**.

Returning to block **352**, in response to an L2 miss, the process proceeds to block **360**, which illustrates L2 cache **230** selecting and initiating eviction of a victim cache line, as discussed further below with reference to FIGS. **5**-**6**. In addition, L2 cache **230** transmits the trailing prefetch request to L3 cache **232**. Consequently, L3 cache **232** accesses its cache directory **292** to determine whether or not the target address specified by the trailing prefetch request hits in cache directory **292** of L3 cache **232** (block **362**). If not, the process passes to block **363**, which is described below. If, however, the trailing prefetch request hits in cache directory **292** of L3 cache **232**, the process proceeds to block **364**, which depicts L3 cache **232** reading the requested cache line of data from cache array **284** of L3 cache **232** and providing the requested cache line to L2 cache **230**. The process then bifurcates and proceeds to blocks **356** and **366**.

As noted above, block **356** depicts L3 cache **232** sending the requested cache line of data to the requesting processor core **202**. Thereafter, the first branch of the process ends at block **376**. Block **366** illustrates L3 cache **232** updating the coherence state of the requested cache line of data in cache directory **292** of L3 cache **232** in accordance with Table III, above. In addition, L3 cache **232** updates replacement field **298** for the requested cache line to indicate second class LRU, meaning that the requested cache line is not likely to again be accessed by the associated processor core **202** and is preferred for replacement in the event of an L3 eviction. As illustrated at block **368**, master **284** of L2 cache **230** also updates the state of the requested cache line of data in cache directory **292** of L2 cache **230**, if necessary, in accordance with Table IV, above. As shown at block **374**, once the victim cache line has been evicted from L2 cache **230**, the cache line of data supplied to processor core **202** is also installed in L2 cache **230** (block **374**). Thereafter, the process terminates at block **376**.

Referring now to block **363**, if a trailing prefetch request misses in L3 cache **232**, master **284** within L2 cache **230** does not immediately transmit the trailing prefetch request to the broader system for service. Instead, at block **363** master **284** first checks whether the trailing prefetch request collides (i.e., has a matching target address) with another memory access request currently being serviced by master **284** of L3 cache

232 (i.e., a leading prefetch request being handled by a prefetch machine 234). If not, the process passes directly to block 370, which is described below. If, however, the trailing prefetch request collides with another memory access request currently being serviced by master 284 of L3 cache 232, then master 284 of L2 cache 230 waits until the other memory access request is resolved, as shown at block 365, and thereafter again checks whether the trailing memory access request hits in cache directory 292 of L3 cache 232, as shown at block 362 and as described above. In this manner, bandwidth on the system interconnects is not unnecessarily consumed by the address and data tenures of prefetch requests, which are necessarily speculative.

Referring now to block 370, master 284 of L2 cache 230 requests access authority and the target memory block from the system coherence manager (e.g., the distributed coherence management system described above) by transmitting an appropriate command 250 to the local instance of interconnect logic 212. In response to receipt of the coherence response (also referred to as combined response (CRESP)) and prefetch data for the trailing prefetch request, master 284 of L2 cache 230 updates the coherence state for the target memory block in its cache directory 292 in accordance with the coherence response (block 372). Master 284 of L2 cache 230 also supplies the target memory block to the requesting processor core 202, as indicated by the process passing through page connector A to block 306. In addition, once eviction of the L2 victim is complete and the prefetch data is received, master 284 of L2 cache 230 updates the cache array 284 of L2 cache 230 with the target memory block (block 374). Thereafter, the process ends at block 376.

It should be noted that in the case of a miss of a trailing prefetch in L3 cache 232, the prefetch data is not installed in L3 cache 232. L3 cache 232 is "skipped" for purposes of data installation because, in most cases, a subsequent demand memory access will be serviced by a higher level of the cache memory hierarchy.

Referring now to FIG. 3E, there is depicted a high level logical flowchart of an exemplary method of performing a trailing prefetch for a store prefetch stream in accordance with one embodiment. The process depicted in FIG. 3E begins at block 380 following receipt at an L2 cache 230 of a trailing prefetch request of a store prefetch stream from the associated processor core 202. The process then proceeds to block 381, which illustrates master 284 of L2 cache 230 accessing its cache directory 292 to determine whether or not the target address specified by the trailing prefetch request hits in cache directory 292 of L2 cache 230. If so, the target memory block is already staged to store-in L2 cache 230, meaning that no prefetching is required. Accordingly, the process terminates at block 392.

Returning to block 381, in response to an L2 miss, the process proceeds to block 382, which illustrates L2 cache 230 selecting and initiating eviction of a victim cache line, as discussed further below with reference to FIG. 6. In addition, L2 cache 230 transmits the trailing prefetch request to L3 cache 232. Consequently, L3 cache 232 accesses its cache directory 292 to determine whether or not the target address specified by the trailing prefetch request hits in cache directory 292 of L3 cache 232 (block 383). If not, the process passes to block 387, which is described below. If, however, the trailing prefetch request hits in cache directory 292 of L3 cache 232, the process proceeds to block 384, which depicts L3 cache 232 reading the requested cache line of data from cache array 284 of L3 cache 232 and sending the requested cache line of data to L2 cache 230. The process then proceeds to block 385.

Block 385 illustrates L3 cache 232 updating the coherence state of the requested cache line of data in cache directory 292 of L3 cache 232 in accordance with Table III, above. In addition, L3 cache 232 updates replacement field 298 for the requested cache line to indicate second class LRU, meaning that the requested cache line is unlikely to again be accessed by the associated processor core 202 and is preferred for replacement in the event of an L3 eviction. Master 284 of L2 cache 230 also updates the state of the requested cache line of data in cache directory 292 of L2 cache 230 in accordance with Table IV, above (block 386). As shown at block 391, once the victim cache line has been evicted from L2 cache 230, the cache line of prefetch data is installed in L2 cache 230 (block 391). Thereafter, the process terminates at block 392.

Referring now to block 387, if a trailing prefetch request misses in L3 cache 232, master 284 of L2 cache 230 does not immediately transmit the trailing prefetch request to the broader system for service. Instead, at block 387 master 284 of L2 cache 230 first checks whether the trailing prefetch request collides (i.e., has a matching target address) with another memory access request currently being serviced by master 284 of L3 cache 232 (i.e., a leading prefetch request being handled by a prefetch machine 234). If not, the process passes directly to block 389, which is described below. If, however, the trailing prefetch request collides with another memory access request currently being serviced by master 284 of L3 cache 232, then master 284 of L2 cache 230 waits until the other memory access request is resolved, as shown at block 388, and thereafter again checks whether the trailing memory access request hits in cache directory 292 of L3 cache 232, as shown at block 383 and as described above. In this manner, bandwidth on the system interconnects is not unnecessarily consumed by the address and data tenures of prefetch requests.

Referring now to block 389, master 284 of L2 cache 230 requests access authority and the target memory block from the system coherence manager (e.g., the distributed coherence management system described above) by transmitting an appropriate command 250 to the local instance of interconnect logic 212. In response to receipt of the coherence response and prefetch data for the trailing prefetch request, master 284 of L2 cache 230 updates the coherence state for the target memory block in its cache directory 292 in accordance with the coherence response (block 390). In addition, once eviction of the L2 victim is complete and the prefetch data is received, master 284 of L2 cache 230 updates the cache array 284 of L2 cache 230 with the target memory block of the trailing prefetch request (block 391). Thereafter, the process ends at block 392.

Referring now to FIG. 4, there is depicted a high level logical flowchart of an exemplary method of performing a processor store in accordance with one embodiment. The illustrated process begins at block 400 in response to receipt by L2 cache 230 of a store request 247 from its associated processor core 202. In response to store request 247, master 284 of L2 cache 230 accesses its cache directory 292 to determine whether or not the target address specified by load request 240 hits in cache directory 292 (block 402). If so, the process then proceeds to block 404, which depicts master 284 of L2 cache 230 reading the requested cache line of data from cache array 284 of L2 cache 230. The process then passes to block 406, which is described below.

Returning to block 402, in response to a determination that the target address of the store request 247 missed in cache directory 292 of L2 cache 230, master 284 initiates eviction of a victim cache line from L2 cache 230, as shown at block 410 and as described further below with reference to FIG. 5.

Master **284** also forwards the target address of store request **247** to L3 cache **232**. In response to receipt of the target address of store request **247**, master **284** of L3 cache **232** accesses its cache directory **292** to determine whether or not the target address specified by load request **240** hits in cache directory **292** (block **420**). If not, the process passes to block **424** and following blocks, which are described below. If, however, the target address of store request **247** hits in cache directory **292** of L3 cache **232**, the process proceeds to block **422**, which depicts master **284** of L3 cache **232** reading the requested cache line of data from cache array **284** of L3 cache **232**. The process then passes to block **406**.

Block **406** determines the master **284** of the L2 or L3 cache memory in which the target address hit determining whether or not it is the highest point of coherency (HPC) for the target memory block associated with the target address. An HPC is defined herein as a uniquely identified device that caches a true image of the memory block (which may or may not be consistent with the corresponding memory block in system memory **108**) and has the authority to grant or deny a request to modify the memory block. Descriptively, the HPC may also provide a copy of the memory block to a requestor in response to an operation that does not modify the memory block. Although other indicators may be utilized to designate an HPC for a memory block, a preferred embodiment of the present invention designates the HPC, if any, for a memory block utilizing selected cache coherence state(s). Thus, assuming the coherence states set forth in Tables I and II, above, an L2 cache **230** or L3 cache **232** is designated as an HPC by holding the target memory block in any of the T, Te, Tn, Ten, M, Me or Mu states.

If the master **284** determines at block **406** that its cache **230** or **232** is the HPC for the target memory block, the process passes to block **412**, which is described below. If, however, the master **284** determines that its cache is not the HPC for the target memory block, for example, because the target address hit in the S or S1 coherence state, then master **284** attempts to claim coherence ownership of the target memory block and assume the designation of HPC by transmitting a DClaim (data claim) operation on the interconnect fabric via interconnect logic **212** (block **408**). Master **284** determines whether the attempt to claim coherence ownership is granted at block **410** by reference to the system coherence response (CRESP) to the DClaim. If the attempt to claim coherence ownership is not granted, which typically means that master **284** has been forced to invalidate its copy of the target memory block by a competing master **284** in another cache hierarchy, the process passes through page connector B to block **424**, which is described below. If, however, the master **284** determines at block **410** that the attempt to claim coherence ownership is successful, master **284** performs any coherence "cleanup" necessary to ensure that it alone has a valid cached copy of the target cache line, as shown at block **412**. The coherence "cleanup" typically entails issuing one or more kill requests on local interconnect **114** and/or system interconnect **110** via interconnect logic **212** to invalidate other cached copies of the target memory block.

Next, at block **414** master **284** of L3 cache **232** updates the coherence state of the target memory block in cache directory **292** of L3 cache **232** in accordance with Table V, below. Although the final L3 coherence state in each case is Invalid (I), the class and rank reflected by replacement field **298** are preferably updated to second class LRU in order to avoid the need to implement "special case" logic to handle the case of cache lines in the I coherence state.

TABLE V

Initial L3 State	Final L3 State
M	I
Mu	I
Me	I
T	I
Te	I
Tn	I
Ten	I
SL	I
S	I
Ig	n/a
In	n/a
I	n/a

As illustrated at block **416**, master **284** of L2 cache **230** also updates the state of the target memory block in cache directory **292** of L2 cache **230** in accordance with Table VI, below. As indicated, the target memory block will have an M or Mu coherency state, depending upon whether sharing of the target memory block should be encouraged. This determination can be made on a number of factors, including the type of store access that updated the target memory block. Further details can be found, for example, in U.S. Pat. No. 6,345,343 and U.S. patent application Ser. No. 11/423,717, which are incorporated herein by reference.

TABLE VI

Initial L2 or L3 State	Final L2 State
M	M or Mu
Mu	M or Mu
Me	M or Mu
T	M or Mu
Te	M or Mu
Tn	M or Mu
Ten	M or Mu
Sl	M or Mu
S	M or Mu
Ig	n/a
In	n/a
I	n/a

The process proceeds from block **416** to block **430**, which is described below.

Referring now to block **424**, master **284** of L2 cache **230** requests the target memory block and permission to modify the target memory block from the distributed system coherence manager by transmitting an appropriate command (e.g., Read-with-intent-to-modify (RWITM)) to the local instance of interconnect logic **212**. Master **284** then updates the coherence state for the target memory block in its cache directory **292** in accordance with the coherence response for its request (block **426**). Assuming the request was successful, master **284** of L2 cache **230** merges the store data **249** received from processor core **202** with the target memory block (block **430**). Thus, master **284** may update one or more granules **290** of the target memory block. In addition, once eviction of the L2 victim is complete, master **284** of L2 cache **230** updates cache array **284** with the target memory block (block **432**). Thereafter, the process ends at block **434**.

Referring now to FIG. **5**, there is depicted a high level flowchart of a process of performing an L2 eviction and casting-in the victim cache line into an L3 victim cache in accordance with the one embodiment. The steps depicted on the left side of FIG. **5** are those performed by an L2 cache, such as L2 cache **230**, and those shown on the right side of FIG. **5** are performed by an L3 victim cache, such as L3 cache

232. Steps are generally shown in chronological order, with time advancing in the direction of arrow **500**.

The illustrated process begins at block **502** in response to an L2 cache miss as shown, for example, at block **310** of FIG. **3** or block **410** of FIG. **4**. In response to the L2 cache miss, L2 cache **230** allocates a CO buffer **295** to perform an L2 eviction and selects a victim cache line for replacement in accordance with a selected replacement policy (e.g., least recently used or a variant thereof), as shown at block **504**. As indicated at block **506**, L2 cache **230** (i.e., master **284** of L2 cache **230**) then reads cache directory **292** of L2 cache **230** to determine whether or not a castout is to be performed, for example, by determining if the selected victim cache line has a data-valid coherence state (e.g., Mx, Tx or Sx, where the "x" refers to any variant of the base coherence state) or a scope-state indication coherence state, such as Ig or In. If not, then the CO buffer **295** allocated to the L2 eviction is deallocated and assumes the "done" state (block **510**). Because the victim cache line contains no valid data that must be preserved, L2 cache **230** can also indicate that the storage location of the victim cache line in the L2 cache array **284** has been evacuated (blocks **512**, **514**) and can be filled with a new cache line of data (i.e., the target cache line of the request of the processor core).

Returning to block **506**, if the L2 cache determines that L2 cache directory **292** indicates that a castout is to be performed, L2 cache **230** does not immediately perform a read of L2 cache array **284**, as is performed in a conventional process. Instead, L2 cache **230** transmits a cast-in command to the L3 cache **232** (block **508**). The cast-in command may contain or be accompanied by the real address of the victim cache line, the L2 coherence state, and the CO buffer ID of the allocated CO buffer **295**.

In response to receipt of the cast-in command, L3 cache **232** reads the coherence state associated with the specified address in its L3 cache directory **292** (block **520**). If the L3 cache directory **292** indicates a data-valid coherence state (block **522**), then the cast-in data already resides in the L3 cache array **284**, and no data update to the L3 cache array **284** is required, as indicated by block **524**. Accordingly, L3 cache **232** signals L2 cache **230** to retire the CO buffer **295** allocated to the L2 eviction by issuing an appropriate command specifying the CO buffer ID, as indicated by the arrow connecting block **522** to block **540**. In addition, as shown at block **530**, L3 cache **232** updates the coherency state of the victim cache line in the L3 cache directory **292** in accordance with Table VII, below (the designation Err in Table VII indicates an error condition). In addition, L3 cache **232** sets the rank and class of the victim cache line inserted into L3 cache **232** to first class MRU. Thereafter, the L3 directory update completes at block **532**.

TABLE VII

Initial	L2 Castout State										
L3 State	M	Mu	Me	T	Te	Tn	Ten	SL	S	Ig	In
M	Err	Err	Err	Err	Err	Err	Err	Err	Err	M	M
Mu	Err	Err	Err	Err	Err	Err	Err	Err	Err	Mu	Mu
Me	Err	Err	Err	Err	Err	Err	Err	Err	Err	Me	Me
T	Err	Err	Err	Err	Err	Err	Err	T	T	T	T
Te	Err	Err	Err	Err	Err	Err	Err	Te	Te	Te	Te
Tn	Err	Err	Err	Err	Err	Err	Err	Tn	Tn	Tn	Tn
Ten	Err	Err	Err	Err	Err	Err	Err	Ten	Ten	Ten	Ten
SL	Err	Err	Err	T	Te	Tn	Ten	Err	SL	Ig	SL
S	Err	Err	Err	T	Te	Tn	Ten	SL	S	Ig	S
Ig	M	Mu	Me	T	Te	Tn	Ten	Ig	Ig	Ig	Ig
In	M	Mu	Me	T	Te	Tn	Ten	SL	S	Ig	In
I	M	Mu	Me	T	Te	Tn	Ten	SL	S	Ig	In

Referring again to block **522**, if L3 cache **232** determines that the address specified by the cast-in command misses in L3 cache array **284**, then L3 cache **232** begins the process of evicting a selected victim cache line from L3 cache array **284** (block **526**), as described further below with reference to FIG. **6**A. L3 cache **232** then provides to L2 cache **230** a status signal referencing the CO buffer ID, thereby indicating that a data move from L2 cache **230** to L3 cache **232** will be performed (block **528**). In addition, as shown at block **530**, L3 cache **232** updates the coherency state of the victim cache line in L3 cache directory **292** in accordance with Table VII, above. Thereafter, the L3 directory update completes at block **532**. Thus, the directory update can be performed in advance of initiation of the data move.

Referring now to block **542**, in response to receipt of the status signal from L3 cache **232** indicating that a data move is to be performed, L2 cache **230** expends the power required to read the selected victim cache line from the L2 cache array **284** into the allocated CO buffer **295**. In response to the read of L2 cache array **284**, L2 cache **230** can indicate that the storage location of the victim cache line in the L2 array has been evacuated (blocks **544**, **546**) and can therefore be filled with a new cache line of data. In addition, L2 cache **230** sends to L3 cache **232** a data ready signal specifying the CO buffer ID in order to indicate that the victim cache line has been read into the allocated CO buffer **295** (block **550**).

In response to the data ready signal, L3 cache **232** initiates a data move of the cast-in data from the CO buffer **295** of L2 cache **230** to L3 cache **232** by issuing to L2 cache **230** a data move command specifying the relevant CO buffer ID (block **552**). In response to receipt of the data move command of L3 cache **232**, L2 cache **230** transfers the data in the specified CO buffer **295** to L3 cache **232**, as indicated at block **554**. In a typical implementation, the victim cache line is transmitted in association with the CO buffer ID. Following the data transfer, L2 cache **230** retires or deallocates the CO buffer **295** allocated to the L2 eviction (block **556**), indicating usage of the CO buffer **295** is complete (block **558**). In response to receipt of the victim cache line and CO buffer ID, L3 cache **232** places the cast-in data into L3 cache array **284** in the location indicated by the CO buffer ID (block **560**), thereby completing the movement of the victim cache line from L2 cache **230** to the cache array of the L3 cache **232** (block **562**).

With reference now to FIG. **6**A, there is illustrated a high level logical flowchart of an L3 eviction in accordance with one embodiment. The process begins at block **600**, for example, in response to initiation of an L3 eviction in response to an L2 cast-in command (as shown at block **526** of FIG. **5**) or in response to a leading prefetch (as shown at block **345** of FIG. **3**C) or in response to an L3 cast-in (as shown at block **1030** of FIG. **10**B or block **1083** of FIG. **10**D). In response to initiation of the L3 eviction, L3 cache **232** (i.e., master **284** of L3 cache **232**) allocates a CO buffer **295** to the L3 eviction and selects a victim cache line for replacement in accordance with a selected replacement policy, as shown at block **602** and as described further below with reference to FIG. **7**A.

As indicated at block **603**-**604**, L3 cache **232** also reads the coherence state and replacement field **298** of the selected victim cache line from L3 cache directory **292** and determines whether to perform castout of the victim cache line, and if so, whether to perform a lateral castout (LCO) to another L3 cache **232** or a traditional castout (CO). Ln many if not most implementations, it is desirable to perform an LCO (i.e., an L3-to-L3 castout) rather than a traditional CO to system memory **108** if possible in order to provide lower latency access to data and avoid consuming system memory bandwidth and power.

In at least one embodiment, the determination of whether to perform a castout is made in accordance with Tables I and

II above based upon the coherence state of the victim cache line. The determination of the type of castout (e.g., LCO or CO) to be performed can be made, for example, based upon the coherence state of the victim cache line, and/or the source from which the cast-in cache line was received by L3 cache **232** and/or the chronology vector **297** of the victim cache line.

For example, in a preferred embodiment, a determination is made at block **603** is to perform an LCO unless the cast-in source was another L3 cache **232**, or the victim cache line selected at block **602** is marked as second class, or the coherence state of the victim cache line is other than Mx, Tx or S1. No LCO is performed for a victim cache line in the S coherence state in order to reduce redundant copies of a cache line and because cache lines in the S coherence state are never provided to a requesting cache by cache-to-cache intervention. Further, in this preferred embodiment, a determination is made at block **604** to perform a CO if no LCO is to be performed and if the victim coherence state is Ig. Doing so ensures that the scope state information indicated by the Ig coherence state is retained. No CO is preferably performed for a "clean" victim cache line in any of the Me, Te, Ten and S1 coherence states.

In response to a determination at block **603** to perform an LCO, the process proceeds from block **603** through page connector C to block **640** of FIG. **6**B, which is described below. If L3 cache **232** decides at block **604** to perform a CO, the process proceeds to block **606**, which is described below. Finally, if L3 cache **232** determines at block **604** that no castout is to be performed, then the CO buffer **295** allocated to the L3 eviction is deallocated and assumes the "done" state (block **610**). Because the victim cache line contains no valid data that must be preserved, the L3 victim cache can also indicate that the storage location of the victim cache line in the L3 array has been evacuated (blocks **612**, **614**) and can be filled with a new cache line of data.

Referring now to block **606**, if L3 cache **232** determines that a CO is to be performed for the victim cache line, then L3 cache **232** reads the victim cache line from cache array **284** into the allocated castout (CO) buffer **295**. L3 cache **232** then indicates that the storage location of the victim cache line in the L3 array has been evacuated (blocks **612**, **614**). In addition, the L3 cache **232** transmits a CO command **270** on the interconnect fabric via interconnect logic **212** (block **616**) and then awaits a combined response (from the process shown in FIG. **6**C) providing a system-wide coherency response to the CO command (block **620**). The activity of the snoopers (e.g., IMCs **206** and snoopers **286** of L2 caches **230** and L3 caches **232**) in response to receipt of the CO command and the generation of the combined response are described below with reference to FIGS. **8-9**, respectively.

In response to receipt of the combined response of the CO command, L3 cache **232** determines whether or not the combined response indicates success of the CO command at block **622**. If not, L3 victim cache **232** waits for a "backoff" time, which can be selected randomly within a predetermined range in order to reduce deadlocks (block **624**). Thereafter, the process returns to block **616**, which has been described. Referring again to block **622**, if the combined response indicates that the CO command was successful, L3 victim cache **232** determines at block **626** whether the castout entails transmission of the victim cache line. For example, if the victim cache line is in the Ig state, meaning that the data is invalid, then no transmission of the data of the victim cache line is to be performed. If, on the other hand, the victim cache line is in the T state, the L3 victim cache will determine that the victim cache line data are to be transmitted to a snooper. If a determination is made that the victim cache line data are to be transmitted, the L3 victim cache **232** transmits the victim cache line data **264** from the CO buffer to the destination (e.g., an IMC **206**) at block **628**. Thereafter, L3 victim cache **232** retires the CO buffer allocated to the L3 eviction (block **630**), giving the CO buffer a "done" status (block **632**). If, however, L3 victim cache **232** determines at block **626** that no transmission of the victim cache line data is to be performed, then the process simply passes from block **626** to blocks **630** and **632**, which have been described.

Referring now to block **640** of FIG. **6**B, in response to a determination that an LCO of the victim cache line is to be performed, then L3 cache **232** reads the victim cache line from cache array **284** into the allocated castout (CO) buffer **295**. L3 cache **232** then indicates that the storage location of the victim cache line in cache array **284** of L3 cache **232** has been evacuated (blocks **642**, **644**). In addition, L3 cache **232**, which can be referred to as the source L3 cache **232**, selects a target or destination L3 cache **232** of the LCO that will receive the castout unless a more favorable snooping L3 cache **232** accepts the castout (block **646**). For example, in one embodiment, the source L3 cache **232** selects the target L3 cache **232** according to the method depicted in FIG. **6**C, which is described below. As shown at block **648**, the source L3 cache **232** broadcasts an LCO command **270** (e.g., of a global scope including all processing nodes **102** of data processing system **100**) on the interconnect fabric via interconnect logic **212** (block **616**), where the LCO command indicates, for example, an address and coherence state of the victim cache line and the identity of the target L3 cache **232**. The source L3 cache **232** then awaits a combined response (from the process shown in FIG. **13**) providing a system-wide coherency response to the LCO command (block **650**). The activity of the snoopers (e.g., IMCs **206** and snoopers **286** of L2 caches **230** and L3 caches **232**) in response to receipt of the CO command and the generation of the combined response are described below with reference to FIGS. **10A-10D** and FIG. **11**, respectively.

In response to receipt of the combined response of the LCO command, the source L3 cache **232** determines whether or not the combined response indicates success of the LCO command at block **652**. If not, the source L3 victim cache **232** determines if the number of times the LCO has been retried has reached an abort threshold (e.g., a predetermined integer having a value of zero or greater) (block **654**). If not, the source L3 cache **232** waits for a "backoff" time, which can be selected randomly within a predetermined range in order to reduce deadlocks (block **656**) and retries the LCO, as indicated by the process returning to block **646** and following blocks, which have been described. Referring again to block **654**, if the abort threshold has been reached, the source L3 cache **232** determines whether to perform a CO (block **658**). If not, the CO buffer **295** allocated to the victim cache line is retired, and the process ends at block **660**. If, however, the source L3 cache **232** determines that a CO is to be performed, the process passes through page connector D to block **616** of FIG. **6**A and following blocks, which have been described.

Referring again to block **652**, if the combined response indicates that the LCO command was successful, the source L3 cache **232** determines at block **670** whether the combined response indicates that the source L3 cache **232** should transmit the victim cache line data to the target L3 cache **232**. For example, if the combined response indicates snooping L3 cache **232** in the LCO broadcast domain holds a valid copy of the victim cache line, then no transmission of the data of the victim cache line is to be performed. If, on the other hand, the combined response indicates that no snooping L3 cache **232** in the LCO broadcast domain holds a valid copy of the victim

cache line, the source L3 cache **232** will determine that the victim cache line data are to be transmitted to the target L3 cache **232**. If a determination is made that the victim cache line data are to be transmitted, the source L3 victim cache **232** transmits the victim cache line data **264** from the CO buffer **295** to the target L3 cache **232** at block **672**. Thereafter, L3 victim cache **232** retires the CO buffer **295** allocated to the L3 eviction (block **674**), giving the CO buffer a "done" status (block **676**). If, however, the source L3 cache **232** determines at block **670** that no transmission of the victim cache line data is to be performed, then the process simply passes from block **670** to blocks **674** and **676**, which have been described.

With reference now to FIG. **7**A, there is illustrated a data flow diagram of an exemplary technique for selecting an entry from a single ordered group containing multiple entries (e.g., N, where N is an integer) each belonging to a respective one of multiple different classes, where each class can contain M entries (wherein M is an integer between 0 and N inclusive). The illustrated process, which assumes a congruence class containing two classes of entries, can be utilized, for example, by an L3 cache **232** to select a victim cache line for eviction from among a plurality of cache lines in a congruence class having entries that can each belong to one of multiple classes, as depicted at block **602** of FIG. **6**A. To accelerate the illustrated process, L3 caches **232** preferably implement the illustrated data flow in hardware.

In general, the exemplary data flow depicted in FIG. **7**A selects a second class entry for eviction from a congruence class based upon the access chronology, if a second class entry is present. If no second class entry is present within the congruence class, the exemplary data flow depicted in FIG. **7**A selects a first class entry for eviction from the congruence class. Because second class entries are subject to attrition through eviction, the exemplary data flow also selects a first class entry for demotion to second class upon each eviction. Thus, the illustrated data flow generates a victim vector **760** that provides a decoded identification of the victim cache line to be evicted from the congruence class, as well as a demote vector **762** that provides a decoded identification of the cache line in the congruence class that is to be demoted from first class to second class.

The illustrated data flow begins at block **700** and then proceeds in parallel to each of five parallel processes depicted at blocks **710-714**, **720-724**, **730**, **732** and **740-784**. Referring first to blocks **710-714**, the depicted process selects a victim cache line from among the second class entries, if any, of the congruence class from which a victim is to be selected. To do so, L3 cache **232** generates a first class mask from class subfield **299** to isolate the first class entries of the congruence class (block **710**). These first class entries are then subject to an inline update to reflect them all as MRU, meaning that the first class entries are all removed from consideration as LRU candidates (block **712**). L3 cache **232** then generates a second class LRU vector that provides a decoded identification of the least recently used second class entry in the congruence class (block **714**).

Referring now to blocks **720-724**, in parallel with the process depicted at blocks **710-714**, the depicted process selects a potential victim cache line from among the first class entries in case the congruence class contains no second class entries from which a victim cache line can be selected. To do so, L3 cache **232** generates a second class mask from class subfield **299** to isolate the second class entry or entries, if any, of the congruence class (block **720**). The second class entry or entries, if any, are then subject to an inline update to reflect them all as MRU, meaning that any second class entry or entries are all removed from consideration as LRU candidates (block **722**). L3 cache **232** then generates a first class LRU vector that provides a decoded identification of the least recently used first class entry in the congruence class (block **724**).

With reference now to blocks **740-744**, in parallel with the process depicted at blocks **710-714** and blocks **720-724**, the depicted process selects an entry from among the first class entries in the congruence class to demote to second class. To do so, L3 cache **232** generates an overall LRU mask from the chronology vector **297** of the congruence class to identify which of the entries of the congruence class is the LRU entry (block **740**). At block **742**, L3 cache **232** performs an inline MRU update to the LRU entry to temporarily remove it from consideration (block **742**). L3 cache **232** then generates an overall LRU+1 vector that provides a decoded identification of the second least recently used entry in the congruence class (block **744**).

In parallel with each of the process depicted at blocks **710-714**, blocks **720-724** and blocks **740-744**, the processes depicted at blocks **730** and **732** respectively determine by reference to class subfields **299** of the congruence class of interest whether or not the congruence class contains any second class entries and whether the congruence class of interest contains any first class entries. As functionally represented by the selector illustrated at reference numeral **750**, L3 cache **232** utilizes the outcome of the determination depicted at block **730** to select as victim vector **760** the second class LRU vector, if the congruence class contains at least one second class entry, and otherwise to select the first class LRU vector. As functionally indicated by the selector depicted at reference numeral **752**, L3 cache **232** also utilizes the outcome of the determination to select either the first class LRU entry or first class LRU+1 entry, if either exists, for demotion to second class. In particular, if a determination is made at block **730** that at least one second class entry was present in the congruence class, the first class LRU entry, if any, is identified by selector **752** for demotion to second class; otherwise, the first class LRU+1 entry, if any, is identified by selector **752** for demotion to second class.

The output of selector **752** is further qualified by selector **754** utilizing the outcome of the determination depicted at block **732**. Thus, if at least one first class entry is present in the congruence class, the vector output of selector **752** is selected by selector **754** as demote vector **762**. In the infrequent case that the congruence class contains no first class entries to demote, selector **754** selects a null vector (e.g., all zeros) as demote vector **762**.

Thus, the data flow depicted in FIG. **7**A rapidly identifies from among a group of entries a first entry containing a victim cache line and an entry subject to class demotion without serializing the identification of these entries with a determination of whether any second class entries are present in the group.

Referring now to FIG. **7**B, there is depicted a high level logical flowchart of an exemplary process of selecting a target of a lateral castout (LCO) in accordance with one embodiment. In the depicted embodiment, it is assumed that data processing system **100** is processing a workload that exhibits a high degree of data sharing, meaning that there is an equal probability of any processing unit requesting any given cache line of data and any processing unit providing the requested cache line of data. Under such operating conditions, it is preferred if a cache line that is the subject of a lateral castout (LCO) is cast-in to an L3 cache **232** that is architecturally close to the home system memory **108** so that if the cache line is subsequently castout to the home system memory **108** a

relatively small amount of system resources (e.g., interconnect bandwidth, SNMs **236** and WIMs **238**) would be utilized in that subsequent castout.

The process depicted in FIG. **7**B begins at block **780** and then proceeds to block **782**, which illustrates the source L3 cache **232** implicitly or explicitly determining, for example, by reference to a hardware setting or a software programmable setting, whether or not random selection of a target L3 cache **232** is enabled. If so, source L3 cache **232** determines, for example, by reference to its BAR facility **235**, the home processing node **102** containing the home system memory **108** of the real address of the victim cache line (block **784**). The source L3 cache **232** then randomly selects a target L3 cache **232** for the LCO from among the pool of L3 caches **232** (other than the source L3 cache **232**) within the home processing node **232** (block **786**). The target L3 cache selection process of FIG. **7**B thereafter terminates at block **790**.

Returning to block **782**, if random targeting is not enabled, the process proceeds from block **782** to block **788**. Block **788** illustrates the source L3 cache **232** selecting as the target L3 cache **232** an L3 cache **232** within the home processing node **102** that is architecturally "close" to the home system memory **108** in terms of the number of resources utilized in communication between the selected target L3 cache **232** and the home system memory **108**. For example, in the exemplary embodiment depicted in FIGS. **1** and **2**, L3 cache **232** determines by reference to BAR facility **235** which processing unit **104** contains the IMC **206** that controls the home system memory **108** and selects the L3 cache **232** of that processing unit **104** as the target L3 cache **232** of the LCO. Following block **788**, the target L3 cache selection process of FIG. **7**B thereafter terminates at block **790**.

Referring now to FIG. **8**, there is depicted a high level logical flowchart of an exemplary process by which each snooper (e.g., IMC **206** or snooper **286** of an L2 cache **230** or L3 cache **232**) receiving a castout (CO) command handles the CO command in accordance with one embodiment. The process begins at block **800** of FIG. **8** and then proceeds to block **802**, which illustrates that if the snooper receiving the CO command is not a memory controller, such as an IMC **206**, then the snooper provides a Null partial response to the CO command (block **804**). The Null partial response indicates that the snooper has no interest in the command or its outcome. If the snooper of the CO command is a memory controller, then the process passes from block **802** to block **806**. Block **806** illustrates the memory controller determining whether or not it is assigned the real address specified by the CO command. If not, the memory controller issues a Null partial response (block **808**).

If, however, the snooping memory controller determines at block **806** that it is assigned the real address specified by the CO command, then the memory controller determines at block **810** whether or not it has sufficient resources (e.g., a queue entry and an available access cycle) available to currently handle the CO command. If not, the memory controller provides a Retry partial response requesting that the CO command be retried (block **812**). If, on the other hand, the snooping memory controller determines that it has sufficient resources currently available to handle the CO command, then the snooping memory controller determines at block **814** whether or not the real address specified by the CO command collides with the address of a pending, previously received command. If so, then the snooping memory controller provides a Retry partial response requesting that the CO command be retried (block **816**).

If the snooping memory controller does not detect an address collision at block **814**, then the snooping memory controller allocates resource(s) for handling the CO command (block **818**) and provides an Ack partial response (block **820**), which acknowledges receipt of the CO command by an interested snooper. Thereafter, the snooping memory controller awaits receipt of the combined response (CRESP) generated by the process of FIG. **9** for the CO command (block **822**). In response to receipt of the combined response of the CO command, the snooping memory controller determines whether or not the combined response indicates success of the CO command at block **824**. If not, the snooping memory controller retires the resource(s) allocated to the CO command (block **826**), and the process ends at block **828**.

Referring again to block **824**, if the combined response indicates that the CO command was successful, the snooping memory controller determines at block **830** whether the combined response indicates that the castout entails transmission of the victim cache line to the snooper. If not, the process proceeds to block **834**, which is described below. If, however, the combined response indicates that the castout entails transmission of the victim cache line to the snooper, the snooping memory controller awaits receipt of the victim cache line data at block **832**. Thereafter, at block **834**, the snooping memory controller updates system memory **108** with control information (e.g., the scope information represented by certain of the coherence states) and the victim cache line data, if any. Thereafter, the process passes to block **826** and **828**, which have been described.

With reference now to FIG. **9** is a high level logical flowchart of an exemplary process by which the partial responses of a castout (CO) command are utilized to generate a combined response in accordance with one embodiment. The illustrated process may be performed, for example, by a predetermined instance of coherence management logic **210**, such as the instance of coherence management logic **210** located in the processing unit **104** of the L3 cache **232** initiating the castout.

The illustrated process begins at block **900** in response to receipt by coherence management logic **210** of a partial response of a snooper to a CO command of an L3 cache **232** and then proceeds to block **902**. Block **902** depicts coherence management logic **210** logging the partial response of the CO command and waiting until all such partial responses have been received and logged. Coherence management logic **210** next determines at block **904** whether any of the partial responses were Retry partial responses. If so, coherence management logic **210** generates and provides to all participants a Retry combined response (block **906**). If none of the partial responses were Retry partial responses, then coherence management logic **210** provides a Success combined response if the partial responses include an Ack partial response (blocks **908** and **910**).

If no Retry or Ack partial response was received for the CO command, coherence management logic **210** determines at block **912** whether the CO command was issued on the interconnect fabric with a global scope including all processing nodes **102**. If so, the process ends with an error condition at block **914** in that no memory controller responded to the CO command as responsible for the real address specified by the CO command. If, however, coherence management logic **210** determines at block **912** that the CO command was issued with a more restricted scope than a global scope including all processing nodes **102**, then coherence management logic **210** generates and provides to all participants a Retry Global combined response indicating that the L3 cache **232** that issued the CO command should retry the CO command with a global scope including all processing nodes **102** of data processing system **100** (block **916**).

Referring now to FIG. **10**A, there is depicted a high level logical flowchart of an exemplary process by which a snooper (e.g., IMC **206** or snooper **286** of an L2 cache **230** or L3 cache **232**) receiving a lateral castout (LCO) command handles the LCO command in accordance with one embodiment. The process begins at block **1000** and then proceeds to block **1002**, which depicts the snooper determining what state the LCO command indicates for the victim cache line. If the LCO command indicates an Mx victim cache line (where x represents any of the variation of the base coherence state), the process proceeds to block **1004**, which represents the handling of an LCO Mx command as described further below with reference to FIG. **10**B. If, on the other hand, the LCO command indicates a Tx or S1 coherence state for the victim cache line, the process proceeds to block **1006**, which depicts the handling of the LCO Tx/S1 command as described further below with reference to FIGS. **10**C-**10**D.

With reference now to FIG. **10**B, there is illustrated a high level logical flowchart of an exemplary process by which a snooper (e.g., IMC **206** or snooper **286** of an L2 cache **230** or L3 cache **232**) coupled to the interconnect fabric handles a lateral castout (LCO) of a modified (i.e., Mx) victim cache line in accordance with one embodiment. The illustrated process begins at block **1010**, which represents receipt by a snooper of an LCO command on the interconnect fabric. As indicated at blocks **1012** and **1014**, any snooper other than an L3 cache **232** (e.g., an L2 cache **230** or IMC **206**) provides a Null partial response (PRESP) to the LCO command because LCO commands target only lateral caches (in this embodiment, other L3 caches **232**). Assuming that the snooper is an L3 cache **232**, the snooping L3 cache **232** determines at block **1016** if the address of the victim cache line specified by the LCO command collides with (i.e., matches) an address of a previously received command still being processed by the snooping L3 cache **232**. If so, the snooping L3 cache **232** provides a Retry PRESP (block **1018**), which will be handled by combining logic as shown in FIG. **11**.

The snooping L3 cache **232** also determines at block **1020** if it is the target L3 cache **232** identified in the LCO command. If not, the snooping L3 cache **232** provides a Null PRESP to the LCO command (block **1014**), regardless of whether it may associate the victim cache line address with an Ig or In coherence state. Assuming now that the snooping L3 cache **232** is the target L3 cache **232** of the Mx LCO command, the target L3 cache **232** determines at block **1022** whether or not a WIM **238** is available within the target L3 cache **232** to handle the Mx LCO command. If not, the target L3 cache **232** provides a Retry PRESP (block **1024**).

If the target L3 cache **232** determines at block **1022** that a WIM **238** is available to handle the Mx LCO command, the target L3 cache **232** provides an Ack (Acknowledge) PRESP confirming its ability to service the Mx LCO command (block **1026**) and allocates an available WIM **238** to handle the Mx LCO command (block **1028**). The allocated WIM **238** initiates an L3 eviction as depicted in FIGS. **6**A-**6**B in anticipation of receiving the data of the modified victim cache line (block **1030**). In addition, the allocated WIM **238** updates the cache directory **292** for the victim cache line in accordance with Table VIII below, applies the demote vector **762** obtained by the process of FIG. **7**A, and marks the victim cache line in replacement field **298** as second class and MRU (block **1032**). As a result, the entry demoted to second class by demote vector **762** is effectively made MRU-1.

TABLE VIII

	LCO Castout State		
Initial L3 State	M	Mu	Me
Ig	M	Mu	Me
In	M	Mu	Me
I (miss)	M	Mu	Me

The allocated WIM **238** in the target L3 cache **232** then awaits the CRESP for the Mx LCO command, as illustrated at block **1034**, and examines the CRESP upon receipt as indicated at block **1036**. If the CRESP does not indicate Success: Target Move, the process terminates with an error at block **1038**. If, however, the CRESP indicates Success: Target Move, the process proceeds from block **1036** to block **1040**, which illustrates the allocated WIM **238** awaiting receipt of the data of the victim cache line from the source L3 cache **232** via the interconnect fabric (block **1040**). Following receipt of the data of the victim cache line, the allocated WIM **238** installs the victim cache line in its cache array **284** once the L3 eviction depicted at block **1030** is complete (block **1042**). Thereafter, the allocated WIM **238** is deallocated, as shown at block **1044**. The process then terminates at block **1046**.

Referring now to FIGS. **10**C-**10**D, there is depicted a high level logical flowchart of an exemplary process by which a snooper (e.g., IMC **206** or snooper **286** of an L2 cache **230** or L3 cache **232**) handles a lateral castout (LCO) of a possibly shared victim cache line in accordance with one embodiment. The illustrated process begins at block **1050**, which represents receipt by a snooper of an LCO command on the interconnect fabric. As indicated at blocks **1052** and **1054**, any snooper other than an L3 cache **232** (e.g., an L2 cache **230** or IMC **206**) provides a Null partial response (PRESP) to the LCO command because LCO commands target only lateral caches (in this embodiment, other L3 caches **232**). Assuming that the snooper is an L3 cache **232**, the snooping L3 cache **232** determines at block **1056** if the address of the victim cache line specified by the LCO command collides with (i.e., matches) an address of a previously received command still being processed by the snooping L3 cache **232**. If so, the snooping L3 cache **232** provides a Retry PRESP (block **1058**).

The snooping L3 cache **232** also determines at block **1060** if the address of the victim cache line specified by the LCO command hits in its cache directory **292** in a Tx or S1 coherence state. If not, the process proceeds to block **1076**, which is described below. If, however, the address of the victim cache line hits in cache directory **292** of the snooping L3 cache **232** in a Tx or S1 coherence state, then the snooping L3 cache **232** is preferred as a recipient of the LCO regardless of whether the snooping L3 cache **232** is designated by the LCO command as the target L3 cache **232**. If an affirmative determination is made at block **1060**, the process passes to block **1062**, which illustrates the snooping L3 cache **232** determining whether or not it has a snoop machine (SNM) **236** available to handle the LCO command. If not, the snooping L3 cache **232** provides a Retry PRESP (block **1064**). If a SNM **236** is available for allocation to the LCO command, the snooping L3 cache **232** provides a TXSL PRESP to indicate the presence of another copy of the victim cache line and that it will act as the recipient of the castout (block **1066**) and allocates a available SNM **236** to handle the LCO command (block **1068**).

The allocated SNM **236** updates the entry in cache directory **292** for the address of the victim cache line in accordance with Table IX below and marks the entry as MRU, leaving the

class of the entry unchanged (block **1070**). Thereafter, the snooping L3 cache **232** deallocates the allocated SNM **236** (block **1072**) and the process terminates at that snooping L3 cache **232** (block **1074**). Thus, in this case, the LCO command is serviced prior to CRESP and without transmission of the victim cache line data by a snooping L3 cache **232** self-selected by coherence state independently of the target L3 cache **232** specified by the LCO command.

TABLE IX

	LCO Castout State				
Initial L3 State	T	Te	Tn	Ten	SL
T	Err	Err	Err	Err	T
Te	Err	Err	Err	Err	Te
Tn	Err	Err	Err	Err	Tn
Ten	Err	Err	Err	Err	Ten
SL	T	Te	Tn	Ten	Err
S	T	Te	Tn	Ten	SL

Referring now to block **1076**, the snooping L3 cache **232** determines whether or not it is the target L3 cache **232** identified in the LCO command. If not, the snooping L3 cache **232** provides a Null PRESP to the LCO command (block **1078**), regardless of whether it may associate the victim cache line address with an Ig, In or S coherence state. Assuming now that the snooping L3 cache **232** is the target L3 cache **232** of the LCO command, the target L3 cache **232** determines at block **1080** whether or not its cache directory **292** indicates that it holds an S copy of the victim cache line. If not, the process proceeds through page connector E to block **1069** of FIG. **10**D, which is described below. If, however, the target L3 cache **232** determines at block **1080** that it holds a copy of the victim cache line in the S coherence state, the target L3 cache **232** determines at block **1082** whether or not a SNM **236** is available within the target L3 cache **232** to handle the LCO command. If not, the target L3 cache **232** provides a Retry PRESP (block **1064**).

If the target L3 cache **232** determines at block **1082** that a SNM **236** is available to handle the LCO command, the target L3 cache **232** provides a Shared PRESP confirming its ability to service the LCO command (in the absence of an available snooping L3 cache **232** holding the victim cache line in the Tx or S1 coherence state) and indicating existence of a shared copy of the victim cache line (block **1084**). In addition, the target L3 cache **232** allocates an available SNM **236** to handle the LCO command (block **1086**). The allocated SNM **236** in the target L3 cache **232** then awaits the CRESP for the LCO command, as illustrated at block **1088**, and examines the CRESP upon receipt to determine if it is the recipient of the castout as indicated at block **1090**. If the CRESP does not indicate Success: Target Merge, no coherence update (or data movement) is required at the target L3 cache **232**. Thus, the target L3 cache **232** deallocates the SNM **236** allocated to handle the LCO command (block **1072**), and the process terminates at block **1074**. If, however, the CRESP indicates Success: Target Merge, the process proceeds from block **1090** to block **1070** and following blocks, which illustrate the handling of the castout at the target L3 cache **232** in the manner previously described.

With reference now to block **1069** of FIG. **10**D, the target L3 cache **232** determines whether the coherence state of the victim cache line specified by the LCO command is S1 and the coherence state specified for the victim cache line address in the cache directory **292** of the snooping L3 cache **232** is Ig. If so, the Ig coherence state is preferably retained in the target L3 cache **232**, and in the depicted embodiment the target L3 cache **232** accordingly provides a Retry PRESP (block **1073**). In other embodiments, the target L3 cache **232** may alternatively permit the LCO command to proceed without retry, but simply discard the data of the victim cache line so that no directory update is made.

In response to a negative determination at block **1069**, the target L3 cache **232** determines at block **1071** whether a WIM **238** is available to handle the LCO command. If not, the target L3 cache **232** provides a Retry PRESP (block **1073**). If the target L3 cache **232** determines at block **1071** that a WIM **238** is available to handle the LCO command, the target L3 cache **232** provides an Ack PRESP confirming its ability to service the LCO command in the absence of availability of a more preferred snooping L3 cache **232** (block **1075**) and allocates an available WIM **238** to handle the LCO command (block **1077**). The allocated WIM **238** in the target L3 cache **232** then awaits the CRESP for the LCO command, as illustrated at block **1079**, and examines the CRESP upon receipt to determine if it is the recipient of the castout, as indicated at block **1081**.

If the CRESP does not indicate Success: Target Move, the LCO command will not complete in the target L3 cache **232** but may complete in a different snooping L3 cache **232**, as previously described. Consequently, the target L3 cache **232** deallocates the WIM **238**, and the process terminates at block **1093**. If, however, the CRESP indicates Success: Target Move, the process proceeds from block **1081** to block **1083**, which illustrates the allocated WIM **238** in the target L3 cache **232** initiating an L3 eviction as depicted in FIGS. **6**A-**6**B in anticipation of receiving the data of the victim cache line (block **1083**). In addition, the allocated WIM **238** updates the entry in cache directory **292** for the victim cache line in accordance with Table VIII above, applies the demote vector **762** obtained by the process of FIG. **7**A, and marks the victim cache line in replacement field **298** as second class and MRU (block **1085**). As a result, the entry demoted to second class by demote vector **762** is effectively made MRU-1.

The WIM **238** in the target L3 cache **232** then awaits receipt of the data of the victim cache line from the source L3 cache **232** via the interconnect fabric (block **1087**). Following receipt of the data of the victim cache line, the allocated WIM **238** installs the victim cache line in its cache array **284** of the target L3 cache **232** once the L3 eviction depicted at block **1083** is complete (block **1089**). Thereafter, the allocated WIM **238** is deallocated, as shown at block **1091**. The process then terminates at block **1093**.

FIG. **11** is a high level logical flowchart of the processing of the coherence responses of a lateral castout (LCO) command in accordance with one embodiment. The illustrated process may be performed, for example, by a predetermined instance of coherence management logic **210**, such as the instance of coherence management logic **210** located in the processing unit **104** of the source L3 cache **232** initiating the LCO.

The illustrated process begins at block **1100** in response to receipt by coherence management logic **210** of a partial response of a snooper to an LCO command of a source L3 cache **232** and then proceeds to block **1102**. Block **1102** depicts coherence management logic **210** logging the partial response of the LCO command and waiting until all such partial responses have been received and logged.

Coherence management logic **210** then determines at block **1108** whether any TXSL PRESP has been received. If so, coherence management logic **210** generates and provides to all participants a Success: Early Merge combined response

indicating that the LCO command completed successfully prior to combined response without data movement (block **1110**).

If no TXSL PRESP has been received, coherence management logic **210** determines at block **1112** whether any Shared PRESP has been received. If so, coherence management logic **210** generates and provides to all participants a Success: Target Merge combined response indicating that the LCO command is to be completed at the target L3 cache **232** by a coherence state update and without transmission of the victim cache line data by the source L3 cache **232** (block **1114**).

If no Shared PRESP has been received, coherence management logic **210** determines at block **1116** whether any Ack PRESP has been received. If so, coherence management logic **210** generates and provides to all participants a Success: Target Move combined response indicating that the LCO command is to be completed at the target L3 cache **232** by an update to the coherence state in the cache directory **292** and, following transmission of the victim cache line data by the source L3 cache **232**, by installation of the victim cache line in cache array **284** (block **1118**).

If no Ack PRESP has been received, coherence management logic **210** determines at block **1120** if any Retry PRESP was received. If so, coherence management logic **210** generates and provides to all participants a Retry combined response that causes the LCO command to be retried or aborted (block **1124**). If a determination is made at block **1120** that no TXSL, Shared, Ack or Retry partial response has been received, then coherence management logic **210** signals that an error has occurred (block **1122**).

As has been described herein, in one embodiment a data processing system includes a plurality of processing units including a first processing unit and a second processing unit coupled by an interconnect fabric. The first processing unit has a first processor core and associated first upper and first lower level caches, and the second processing unit has a second processor core and associated second upper and lower level caches. In such a system, in response to a data request, a victim cache line is selected to be castout from the first lower level cache. The first processing unit accordingly issues a lateral castout (LCO) command on the interconnect fabric, where the LCO command identifies the victim cache line to be castout from the first lower level cache and indicates that a lower level cache is an intended destination of the victim cache line. In response to a coherence response to the LCO command indicating success of the LCO command, the victim cache line is removed from the first lower level cache and held in the second lower level cache.

In at least one embodiment, the LCO command specifies a particular target lower level cache that will accept the castout if the broadcast of the LCO command does not discover a more preferred recipient. If, however, the broadcast of the LCO command opportunistically discovers a more preferred lower level cache that permits the castout to be performed without data movement, that castout indicated by the LCO command is handled by the more preferred lower level cache, thus avoiding displacement of an existing cache line by the castout and preserving storage capacity in the more preferred lower level cache. In at least one embodiment, the target lower level cache is selected on the basis of architectural proximity to the home system memory assigned the real address of the victim cache line to be castout by the LCO command. In various embodiments, the selection of the target lower level cache can either directly select a particular target lower level cache based on architectural proximity to the home system memory or can identify of pool of lower level caches that are architecturally proximate to the home system memory and then further select the target lower level cache from the pool.

In at least one embodiment, the LCO command and its associated coherence responses are broadcast via the same interconnect fabric utilized to transmit memory access requests (and associated coherence responses) of like broadcast scope.

The described castout behavior utilizing LCOs can promote performance in a multiprocessor data processing system operating under a variety of workloads. For example, if many processor cores are operating on a shared data set, the behavior of the lower level caches adapts to approximate that of a large shared cache so that data movement and redundant storage of particular cache lines are reduced. Alternatively, if one processor core is operating under a heavy workload and other nearby processor cores have relatively light workloads, the processor core operating under a heavy workload gradually consumes capacity of lower level caches of other processor cores, providing in effect another level of cache memory for the heavily loaded processor core. Further, in the case where each processor core is operating on its own data set, a dynamic equilibrium is achieved in the utilization of each lower level cache by the associated processor core and the other processor cores.

In at least one embodiment, cache management in a victim cache in a cache hierarchy of a processor core is performed by receiving a castout command identifying a victim cache line castout from another cache memory and thereafter holding the victim cache line in a cache array of the victim cache. If the other cache memory is a higher level cache in the cache hierarchy of the processor core, the victim cache line is marked in the victim cache so that it is less likely to be evicted by a replacement policy of the victim cache; otherwise, the victim cache line is marked in the victim cache so that it is more likely to be evicted by the replacement policy of the victim cache.

In at least one embodiment, cache management is enhanced by an enhanced multi-class victim selection technique in which a victim cache line is selected from among a plurality of cache lines in a congruence class of a cache memory for replacement, where each of the cache lines belongs to one of multiple classes including at least a first class and a second class. According to the disclosed technique, if the congruence class contains a cache line belonging to the second class, a cache line of the congruence class belonging to the second class is preferentially selected as a victim cache line based upon access order. If the congruence class contains no cache line belonging to the second class, a cache line belonging to the first class is selected as the victim cache line based upon access order. The selected victim cache line is then evicted from the cache memory.

While one or more embodiments have been particularly shown and described, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the spirit and scope of the invention. For example, although aspects of the present invention have been described with respect to data processing system hardware, it should be understood that one or more embodiments of the present invention may alternatively be implemented as a program product for use with a data processing system. Such program product(s) include(s) a computer readable medium that stores or encodes program code that directs the functions of the present invention. The computer readable medium may be implemented, for example, as a tangible storage medium (e.g., CD-ROM, DVD, diskette or hard disk, system memory, flash memory, etc.) or communication media, such as digital and analog networks.

As an example, the program product may include data and/or instructions that when executed or otherwise processed on a data processing system generate a logically, structurally, or otherwise functionally equivalent representation (including a simulation model) of hardware components, circuits, devices, or systems disclosed herein. Such data and/or instructions may include hardware-description language (HDL) design entities or other data structures conforming to and/or compatible with lower-level HDL design languages such as Verilog and VHDL, and/or higher level design languages such as C or C++. Furthermore, the data and/or instructions may also employ a data format used for the exchange of layout data of integrated circuits and/or symbolic data format (e.g. information stored in a GDSII (GDS2), GL1, OASIS, map files, or any other suitable format for storing such design data structures).

What is claimed is:

1. A method of data processing in a data processing system including a plurality of processing units including a first processing unit and a second processing unit coupled by an interconnect fabric, wherein the first processing unit has a first processor core and associated first upper and first lower level caches and the second processing unit has a second processor core and associated second upper and lower level caches, said method comprising:

in response to a data request, selecting a victim cache line to be castout from the first lower level cache;

selecting a target lower level cache of one of the plurality of processing units other than the first processing unit based upon architectural proximity of the target lower level cache to a home system memory to which an address of the victim cache line is assigned;

the first processing unit issuing a lateral castout (LCO) command on the interconnect fabric, wherein the LCO command identifies the victim cache line to be castout from the first lower level cache and indicates that the target lower level cache is an intended destination of the victim cache line; and

in response to a coherence response to the LCO command indicating success of the LCO command, removing the victim cache line from the first lower level cache and holding the victim cache line in the second lower level cache, wherein the first and second lower level caches are at a same cache hierarchy level.

2. The method of claim **1**, wherein the first and second lower level caches are victim caches.

3. The method of claim **1**, wherein:

the victim cache line is a first victim cache line; and

the method further comprises evicting a second victim cache line from the second lower level cache to make room for the first victim cache line in the second lower level cache.

4. The method of claim **1**, wherein said lateral castout command identifies the second lower level cache as the target lower level cache.

5. The method of claim **1**, and further comprising:

in response to a coherence response to the LCO command indicating success of the LCO command, the first processing unit transmitting the victim cache line to the second lower level cache.

6. The method of claim **1**, wherein selecting a target lower level cache comprises:

determining a pool containing multiple lower level caches architecturally proximate to the home system memory; and

selecting the target lower level cache from the pool.

7. The method of claim **1**, wherein selecting a target lower level cache comprises:

selecting the target lower level cache utilizing a base address register facility.

8. A data processing system, comprising:

an interconnect fabric;

a plurality of processing units coupled to the interconnect fabric, the plurality of processing units including a first processing unit and a second processing unit, wherein the first processing unit has a first processor core and associated first upper and first lower level caches, and wherein the second processing unit has a second processor core and associated second upper and lower level caches, wherein the first and second lower level caches are at a same cache hierarchy level; and

a home system memory coupled to the interconnect fabric, wherein the home system memory is assigned a plurality of addresses including an address;

wherein the first processing unit, in response to a data request, selects a victim cache line associated with the address to be castout from the first lower level cache, selects a target lower level cache of one of the plurality of processing units other than the first processing unit based upon architectural proximity of the target lower level cache to the home system memory to which the address of the victim cache line is assigned, and issues a lateral castout (LCO) command on the interconnect fabric, the LCO command identifying the victim cache line to be castout from the first lower level cache and indicating that the target lower level cache is an intended destination of the victim cache line; and

wherein responsive to a coherence response to the LCO command indicating success of the LCO command, the first processing unit removes the victim cache line from the first lower level cache and the second lower level cache holds the victim cache line.

9. The data processing system of claim **8**, wherein the first and second lower level caches are victim caches.

10. The data processing system of claim **8**, wherein:

the victim cache line is a first victim cache line; and

the second lower level cache evicts a second victim cache line to make room for the first victim cache line in the second lower level cache.

11. The data processing system of claim **8**, wherein said lateral castout command identifies the second lower level cache as the target lower level cache.

12. The data processing system of claim **8**, wherein the first processing unit transmits the victim cache line to the second lower level cache in response to a coherence response to the LCO command indicating success of the LCO command.

13. The data processing system of claim **8**, wherein the first processing unit selects the target lower level cache by determining a pool containing multiple lower level caches architecturally proximate to the home system memory and selecting the target lower level cache from the pool.

14. The data processing system of claim **8**, wherein the first processing unit includes a base address register facility and select the target lower level cache utilizing the base address register facility.

15. A processing unit for a data processing system including a home system memory and a plurality of processing units coupled by an interconnect fabric, wherein the home system memory is assigned a plurality of addresses including an address, the processing unit comprising:

the processing unit has a first processor core and associated first upper and first lower level caches;

wherein the processing unit, in response to a data request, selects a victim cache line associated with the address to be castout from the first lower level cache, selects a target lower level cache of one of the plurality of processing units other than the first processing unit based upon architectural proximity of the target lower level cache to the home system memory to which the address of the victim cache line is assigned, and issues a lateral castout (LCO) command on the interconnect fabric, the LCO command identifying the victim cache line to be castout from the first lower level cache and indicating that the target lower level cache is an intended destination of the victim cache line; and

wherein responsive to a coherence response to the LCO command indicating success of the LCO command, the first processing unit removes the victim cache line from the first lower level cache for storage in a second lower level cache, wherein the first and second lower level caches are at a same cache hierarchy level.

16. The processing unit of claim **15**, wherein the first and second lower level caches are victim caches.

17. The processing unit of claim **15**, wherein said lateral castout command identifies the second lower level cache as the target lower level cache.

18. The processing unit of claim **15**, wherein the first processing unit transmits the victim cache line to the second lower level cache in response to a coherence response to the LCO command indicating success of the LCO command.

19. The processing unit of claim **15**, wherein the processing unit selects the target lower level cache by determining a pool containing multiple lower level caches of the data processing system that are architecturally proximate to the home system memory and selecting the target lower level cache from the pool.

20. The processing system of claim **15**, wherein the processing unit includes a base address register facility and select the target lower level cache utilizing the base address register facility.

21. The method of claim **1**, wherein:

the plurality of processing units includes a third processing unit having associated third upper and third lower level caches, wherein the third lower level cache is architecturally proximate to the home system memory;

the first processing unit issuing the lateral castout (LCO) command includes the third processing unit indicating in the LCO command that the third lower level cache is the target lower level cache;

in response to the LCO command, the second lower level cache providing a partial response indicating the second lower level cache currently holds a copy of the victim cache line;

the method further includes generating the coherence response based in part on the partial response; and

removing the victim cache line from the first lower level cache and holding the victim cache line in the second lower level cache includes removing the victim cache line from the first lower level cache and holding the victim cache line in the second lower level cache without transmitting the victim cache line to the second lower level cache.

22. The method of claim **21**, and father comprising:

in response to the lateral castout (LCO) command, the second lower level cache updating a directory entry of the second lower level cache associated with the victim cache line without waiting to receive the coherency response.

23. The data processing system of claim **8**, wherein:

the plurality of processing units further includes a third processing unit having associated third upper and third lower level caches, wherein the third lower level cache is architecturally proximate to the home system memory;

the lateral castout (LCO) command indicates in the LCO command that the third lower level cache is the target lower level cache;

in response to the LCO command, the second lower level cache provides a partial response indicating the second lower level cache currently holds a copy of the victim cache line;

the data processing system generates the coherence response based in part on the partial response; and

the first lower level cache refrains from transmitting the victim cache line to the second lower level cache.

24. The data processing system of claim **23**, wherein:

the second lower level cache, in response to the lateral castout (LCO) command, updates a directory entry of the second lower level cache associated with the victim cache line without waiting to receive the coherency response.

25. The processing unit of claim **15**, wherein:

a third lower level cache is architecturally proximate to the home system memory;

the lateral castout (LCO) command indicates in the LCO command that the third lower level cache is the target lower level cache; and

the first lower level cache refrains from transmitting the victim cache line to the second lower level cache.

* * * * *